

<b>Calendar</b> .....	<b>11-2</b>
Opening Calendar .....	11-2
Creating Schedule Events.....	11-2
Setting Day Off.....	11-4
Viewing/Editing Schedule Events.....	11-4
Calendar Functions.....	11-5
<b>Alarms</b> .....	<b>11-6</b>
Setting Alarm .....	11-6
<b>Calculator</b> .....	<b>11-7</b>
<b>Notepad</b> .....	<b>11-8</b>
Notepad Functions .....	11-8
<b>Count Down Timer</b> .....	<b>11-9</b>
<b>Voice Recorder</b> .....	<b>11-9</b>
<b>Bar Code Reader</b> .....	<b>11-10</b>
Scanning Barcodes .....	11-10
Viewing/Editing Scanned Data .....	11-11
Using Barcode Data.....	11-11
<b>One Touch Guide</b> .....	<b>11-12</b>




# Calendar


View by day, week or month; set Alarms for events.

## Opening Calendar

1 

Current month appears.

- When a date with schedule events is selected, up to four events appear.
- Press  or  to display previous/next month calendar.
- To switch Monthly/Weekly view:  
 P.11-5



One Month Window

### Note


- Alternatively, **Main Menu** ► **Tools** ► **Calendar**.


## Creating Schedule Events

Save up to 100 entries.

1 



2  to highlight a date

→  [Menu] → **New Entry**



3 Select an item (See below)




Item	Operation/Description
Summary	> Enter title or content
Category	Select an event type; icon appears in Standby > Select a category
Start	> Enter date and time the schedule event starts
End	> Enter date and time the schedule event ends
Description	> Enter event description
Repetition	> Select a repeat type ( → Enter repeating time)


Item	Operation/Description
Reminder	> Select an alarm type
Location	> Enter location
Schedule Tone	> Select an item <ul style="list-style-type: none"> <li>· <b>Default Tone</b></li> <li>· <b>Ring Songs-Tones</b> or <b>Music</b> → Highlight a file →  [Set]</li> </ul>
Schedule Volume	>  to adjust volume
Notification Light	Set schedule alarm notification light color > Select a color or <b>OFF</b>

#### 4 [Save]

##### Schedule Icon

Selected icon in Category appears in Standby.

Example:  (Meeting),  (Anniversary),  (Birthday)



- If nothing selected,  appears.
- Icon disappears after scheduled event has passed.

##### Note






- Schedule events between 00:00 on 2000/01/01 and 23:59 on 2099/12/31 can be saved on handset.

## At Reminder Time

### Schedule Tone sounds and Notification Light flashes.

- 1 When Schedule Tone sounds,  Schedule Tone stops and Schedule Event List appears.
- 2  to view details

### Canceling Schedule Tone

- Press  to return to Standby.
- Press  [Stop] to return to previous menu.
- Press any key except for ,  [Stop],  [View] or  to cancel Schedule Tone without returning to Standby. Press  to view detailed schedule.

##### Note

- Schedule Tone does not sound in the following cases:
  - During a call (Notification appears and handset vibrates)
  - In Manner Mode (Manner Mode settings take priority)
  - When handset power is turned off
  - For entries invalidated by Time Correction



## Setting Day Off

- Day Off dates appear in red.

1 

2 (Highlight a date →)  [Menu] → **Set Day Off**

3 Select an item (See below)

Item	Operation/Description
Weekly	> Check the dates →  [OK]
Today*	> <b>Once</b> or <b>Yearly</b>
Reset All	Reset all Day off dates > 

\* To cancel selection: **Reset Holiday**

## Viewing/Editing Schedule Events

- Holidays appear in red.




1  → Select a date




Schedule Event List

2 Select a schedule event

Detailed schedule appears.

- Press  to switch Schedule tab and Contents tab.
- To edit:  [Edit] → Edit selected items  
( From Step 3 on P.11-2)



Schedule Event Details

## Calendar Functions

From 

### Switch Calendar View

<Default> One Month

>  [Menu] → *View Format* → *One Month* or *One Week*

- Select *One Week* view to see daily schedules.

### Search Specific Day











>  [Menu] → *Go to Date* → Enter date

### Set Week Start Day

>  [Menu] → *Start Week From* → Select a day

### Delete Schedule Events

> Follow the steps below

Item	Operation/Description
One	> Select a date → Highlight an event →  [Menu] → <i>Delete</i> → 
Scheduled Events*	> Highlight a date →  [Menu] → <i>Delete</i> → <i>Day</i> →  → 
Past Events*	> Highlight a date →  [Menu] → <i>Delete</i> → <i>Past</i> →  → 
All	>  [Menu] → <i>Delete</i> → <i>All</i> →  [YES] → Enter Phone Password

\* Repetitive entries cannot be deleted.

### Calendar Memory Status

>  [Menu] → *Memory Status*

## Tip

- Send Schedule Data via Infrared (☞ P.9-3)

# Alarms

When scheduled time arrives, alarm tone sounds and animation appears on Display. Notification Light illuminates.


## Setting Alarm

Set up to five alarms. Alarm tone sounds at the specified time once, everyday or weekly as set.

-  appears in Standby when Alarm is set.





Main Menu ▶ Tools ▶ Alarms

1 Select an Alarm



2 Select an item (See below)

Item	Operation/Description
Alarm ON/OFF	Activate or cancel Alarm > <b>ON</b> or <b>OFF</b>
Time	> Enter time

Item	Operation/Description
Repetition	> Select a repeat type ( → For <b>Weekly</b> , check days →  [OK])
Alarm Tone	> Select an item <ul style="list-style-type: none"> <li>· <b>Default Tone</b></li> <li>· <b>Ring Songs-Tones</b> or <b>Music</b> → Highlight a file* → [Set]</li> </ul>
Set Alarm Snooze	Alarm Tone sounds for 60 seconds, repeating up to five times at specified intervals > <b>ON</b> or <b>OFF</b> ( → For <b>ON</b> , enter interval)
Alarm Volume	>  to adjust volume
Picture	Select image to appear > Select an item <ul style="list-style-type: none"> <li>· <b>Default Picture</b></li> <li>· <b>Pictures</b> → Highlight a still image → [Set]</li> </ul>
Set Alarm Vibration	Select Vibration type > Select pattern or <b>OFF</b>
Notification Light	Select Notification Light color > Select a color or <b>OFF</b>
Set Alarm Priority	Set Manner Mode or Alarm priority > <b>Manner Mode Prioritized</b> or <b>Alarm Prioritized</b>


\* When selecting an SMC file, highlight a Play Point → [Set]

3 [Save]

## At Alarm Time

Alarm Tone sounds, Notification Light flashes and image appears on Display.



### 1 Press any key

Alarm stops and confirmation window appears.  
(When pressing , confirmation does not appear.)



- Alarm stops automatically after 60 seconds of inactivity, and confirmation window appears.


### ■ Cancel/Reactivate Alarm

> **Main Menu** ► **Tools** ► **Alarms** ► Highlight an alarm ►  **[Menu]**  
► **Alarm ON** or **Alarm OFF**

- Activate a canceled Alarm to apply previous settings.
-  appears for set alarms;  for unset/canceled ones.

### Snooze Function

If **ON**, press any key except ; confirmation appears. To cancel Alarm, press  **[Stop]**.

- When pressing  to stop alarm, confirmation does not appear.  
(Snooze function is still active.)













### Note

- Alarm Tone does not sound in the following cases:
  - During a call (Notification appears and handset vibrates)
  - In **Manner Mode Prioritized** (Manner Mode settings take priority)
  - When handset power is turned off
  - For entries invalidated by Time Correction

## Calculator

Calculates up to 10 digits.

**Main Menu** ► **Tools** ► **Calculator**

Operation	Assigned key
Number (0 - 9)	 - 
+	
-	
x	
÷	
=	
Decimal point	
Clear	 or 
Toggle + and -	
%	






### ■ Enter Negative Numbers

- > Enter number, then 
- Press  to toggle negative/positive value.

### Example:

**-17+28.5=11.5**

# Notepad


Main Menu ► Tools ► Notepad

1 [Menu] → **New**

2 Enter text

New note is added to the top of the list.

- Up to 64 characters can be entered.



Notepads Window

## Notepad Functions

From ► Main Menu ► Tools ► Notepad

### Edit Notes

> Select a note → [Edit] → Edit text

- Edited note is overwritten.

### Delete Notes

> Highlight a note → [Menu] → **Delete** → **One** or **All** →

[YES] ( → For **All**, enter Phone Password)

### Note Property

> Highlight a note → [Menu] → **Property**

### Insert Notes into Message Text

> Highlight a note → [Menu] → **Send** → **Send via S! Mail** or

**Send via SMS** → Enter mail address, etc. (S! Mail: From Step 2 on



P.12-4/SMS: From Step 2 on P.12-8) → [Send]




## Count Down Timer

Alarm Tone sounds, handset vibrates and Notification Light flashes when specified time elapses.


Main Menu ► Tools ► Count Down Timer

- 1 Enter time
- 2  [Start]
  - To pause:  [Stop]

### ■ Stop Alarm Tone


- > When Alarm tone sounds,  to stop
- Alarm stops automatically after 30 seconds.

#### Note





- Incoming calls/other alarms do not interfere with timer operation. However, if timer reaches 00:00 while other functions are active, alarm does not sound.
- Alarm tone volume and vibration pattern follow Assign Ringtone ( P.15-2).


## Voice Recorder

Record voice memos.

- Record for up to 60 seconds each.
- Recording conversation during a call:  P.2-9

Main Menu ► Tools ► Voice Recorder

- 1  Recording starts.
- 2  to stop recording
  - To playback: 
- 3  [Save]  
Recorded sounds are saved in Ring Songs-Tones folder.



#### Note

- Sounds recorded by Voice Recorder cannot be set as Alarm, Ringtone or Schedule Tones.

## Bar Code Reader

Scan barcodes (JAN) or QR Codes with built-in camera.  
Access websites, send messages, etc. from QR Codes.

### JAN Codes

JAN Code is a one-dimensional bar code denoting numerals with bars and spaces of different widths.

### QR Codes

QR Code is a two-dimensional bar code containing information.

Example: SoftBank mobile phones



## Scanning Barcodes

- Up to ten items can be saved.
- For split data, up to 16 QR Codes can be scanned at a time and saved as one item.

Main Menu ► Bar Code ► Scan Barcodes

### 1 Frame barcode in the center of Display

- To adjust Display brightness: or
- To zoom:
- To use Focus Lock:

### 2

Scanning starts, and scanned results appear when completed.

- For split data, → Repeat Step 1 and 2

### 3 [Save]

- To start over: → → Go to Step 2

#### Note

- Handset cannot read barcodes or two-dimensional codes other than JAN/QR Codes.
- Some barcodes may be unreadable.
- Barcode recognition may be slow. Hold handset steady while scanning.
- Brightness can be adjusted while scanning; however, zoom level cannot be changed.
- Saved items are automatically named "yyymmdd\_hhmmss" unless changed. (yy: year, mm: month, dd: day, hh: hour, mm: minute, ss: second)
- Barcodes may not be correctly read owing to scratch, dirt, damage, quality of printed material, light reflection, or QR code version.

## Viewing/Editing Scanned Data

Main Menu ► Bar Code ► Saved Data List

### 1 View Saved Data

Select an item

#### Edit Title

Highlight an item →  [Menu] → **Rename** → Edit title

### Delete Saved Data







> In Step 1, highlight an item →  [Menu] → **Delete One** → 

## Using Barcode Data

From ► Main Menu ► Bar Code ► Saved Data List

### Use URLs/Mail Addresses/Phone Numbers

> Select an item → Follow the steps below

Item	Operation/Description
URL ( <a href="http://">http://</a> or <a href="https://">https://</a> )	Connect to websites; add to Bookmarks (  P.13-8)
URL ( <a href="rtsp://">rtsp://</a> )	Streaming; add to Bookmarks
Mail Address	Create S! Mail (  P.12-4); save to Phone Book (  P.4-3)
Phone Number	Make calls; create messages* (S! Mail:  P.12-4/SMS:  P.12-8); save to Phone Book (  P.4-3)
Phone Book Data (MEMORY: text)	Save to Phone Book <ul style="list-style-type: none"><li>● Save <b>MEMORY</b>: text only</li><li>● Saved to <b>Phone</b> regardless of <b>Save Settings</b> selection</li></ul>

\* SoftBank handset numbers only

## ■ Insert Scanned Text into Messages

- > Select an item → [Menu] → *Paste Data & Create Mail*  
 → *S! Mail* or *SMS* → Create message (S! Mail: From Step 2 on P.12-4/SMS: From Step 2 on P.12-8)

## ■ Copy Text from Scanned Results

- > Select an item → [Menu] → *Copy* → Follow the steps below

Item	Operation/Description
All Text	> [All] → [ ]
Selected Text	> Place cursor before (or after) text to copy → [ ] →
	Place cursor after (or before) text to copy → [ ]

# One Touch Guide

Access One Touch Guide for instructions to key operations.

## Main Menu ▶ Tools ▶ One Touch Guide

### 1 Select a function

Instructions appear.

- Press [ ] or [ ] to view previous or next information.



Example:  
Magnifying Loupe

### Note

- Alternatively, view from Shortcuts (From P.1-19) or Private Menu (From P.1-20).