

<b>Calendar &amp; Tasks .....</b>	<b>11-2</b>
Calendar .....	11-2
Tasks .....	11-6
<b>Alarms .....</b>	<b>11-8</b>
Using Alarms .....	11-8
<b>Wakeup TV .....</b>	<b>11-10</b>
Using Wakeup TV .....	11-10
<b>Charging Theater .....</b>	<b>11-12</b>
Using Charging Theater .....	11-12
<b>Relaxation Time .....</b>	<b>11-13</b>
Playing Animation with Music & Illumination .....	11-13
<b>Household Accounts .....</b>	<b>11-14</b>
Managing Household Expenses ...	11-14
<b>Calculator .....</b>	<b>11-18</b>
Using Calculator .....	11-18
<b>Expenses Memo .....</b>	<b>11-19</b>
Adding Expenses .....	11-19
<b>Osaifu-Keitai® .....</b>	<b>11-20</b>
Osaifu-Keitai® (Japanese) .....	11-20
Locking IC Card .....	11-21
<b>Simulated Call .....</b>	<b>11-24</b>
Faking Incoming Calls .....	11-24
<b>Stopwatch .....</b>	<b>11-25</b>
Using Stopwatch .....	11-25
<b>Countdown Timer .....</b>	<b>11-26</b>
Using Countdown Timer .....	11-26
<b>World Clock .....</b>	<b>11-27</b>
Opening World Clock .....	11-27

<b>Hour Minder .....</b>	<b>11-28</b>
Using Hour Minder .....	11-28
<b>Pedometer .....</b>	<b>11-29</b>
Using Pedometer .....	11-29
<b>Compass .....</b>	<b>11-31</b>
Using Compass .....	11-31
<b>S! GPS Navi .....</b>	<b>11-32</b>
Using S! GPS Navi .....	11-32
<b>Document Viewer .....</b>	<b>11-35</b>
Opening PC Documents .....	11-35
<b>Notepad .....</b>	<b>11-36</b>
Saving Text .....	11-36
<b>ASCII Art .....</b>	<b>11-37</b>
Using ASCII Art .....	11-37
<b>Voice Recorder .....</b>	<b>11-38</b>
Recording/Playing Voice .....	11-38
<b>Scan Barcode .....</b>	<b>11-39</b>
Scanning Barcodes .....	11-39
<b>Create QR Code .....</b>	<b>11-40</b>
Creating QR Codes .....	11-40
<b>Scan Card .....</b>	<b>11-41</b>
Scanning Business Cards .....	11-41
<b>Scan Text .....</b>	<b>11-42</b>
Scanning Text .....	11-42
<b>Kanji/English Grabber .....</b>	<b>11-43</b>
Using Kanji/English Grabber .....	11-43
<b>Additional Functions .....</b>	<b>11-44</b>
<b>Troubleshooting .....</b>	<b>11-59</b>

# 11

## Handy Extras

# Calendar

## Opening Calendar

- 1 ➔ **Tools** ➔ ➔ In PIM/  
Life menu, **Calendar** ➔



Calendar Window

- Press to toggle Calendar view.

## Key Assignments

### ■ All Views

Open Previous Page	
Open Next Page	
Open Help	

### ■ 1Month/3Month View

Select Date	
Go to Current Date	

### ■ 6Month View

Go to Current Month	
Select Month	

### ■ Week View


Select Date	
Select Time Block	

## Spinguru Log Calendar (Spinguru Log)

Long Press in Calendar window to switch to Spinguru Log Calendar (Spinguru Log). Select a date and press to save/check schedules, view operation history (mail records, call log, etc.), and more.



Spinguru Log Menu



Timeline Window



## Opening Help

[Spinguru Log Menu]/[Timeline Window] ➔ **Explain Operation** ➔

- To return, press .

## Returning to Calendar Window

[Spinguru Log Menu] (Long)  
Accessing Operation History, Etc.  
[Timeline Window] (Long)

## Advanced

- Changing default view
- Jumping to specified date
- Changing date color
- Selecting task view option
- Adding stamps (1Month/3Month View)
- Hiding schedules
- Saving additional holidays
- Hiding/showing holidays (P.11-44)

## Saving Schedules

Follow these steps to save subject, Category, start/end date/time, Alarm and schedule details:


(Enter Subject or Description to save entry.)

- 1 In Calendar window, select date ➡ ●



- 2 <Add New Entry> ➡ ●

- 3 Enter subject ➡ ●



- 4 ● Preset ➡ Select Category ➡ ●

- 5 Enter start date/time ➡ ●



- 6 End: ➡ ● ➡ Enter end date/time ➡ ●

- 7 Alarm: ➡ ●

- 8 Alarm Time: ➡ ● ➡ Select time ➡ ● ➡ Y

- 9 Description: ➡ ● ➡ Enter schedule details ➡ ●

- 10 Y ➡ Saved

### Selecting Category from History

In 4, ● History ➡ Select Category ➡ ● ➡ From 5

### Selecting Custom Category

In 4, ● Definable ➡ Select Category ➡ ● ➡ From 5

### All-Day Schedule

In 5, ● ➡ ● ➡ From 5

### Custom Alarm Time

In 8, Alarm Time: ➡ ● ➡ Other ➡ ● ➡ Enter date/time ➡ ● ➡ Y ➡ From 5

## Advanced

- Setting Location
- Creating Categories
- Saving repetitive schedules
- Editing entries
- Changing Alarm tone/video & duration
- Changing Alarm volume
- Selecting Vibration option
- Changing illumination settings (And more on P.11-44 - 11-45)

**At Alarm Time**

Alarm activates; sounds/vibrates by related settings.

**Stopping Alarm to Return to Standby**

- While Alarm sounds/vibrates, press or .

**Stopping Alarm to Open Schedule**

- While Alarm sounds/vibrates, press a key other than , , or .

**When Another Function is Active**

- Alarm may not activate until handset returns to Standby.

**Incoming Calls**

- Active Alarm stops for incoming calls. Information window opens after handset returns to Standby.

**Opening Schedules/Tasks**

- In Calendar window, select date**



Schedule List

- Select schedule or task**
- Standby returns**

**Opening Task List**

In , select task **Go to Tasks**

**Accessing Secret Entries**

[Calendar Window] **Unlock Temporarily** **Enter Handset Code**

**Opening Related Message**

Open schedule-related messages saved from Messaging message list.

- In schedule list, select schedule**
- Related Mail**
  - Related message opens.
  - To return to schedule window, press .

**Deleting Message from Schedule**

After , **Related Mail:** **Yes**

**Advanced**

1

- Searching entries
- Checking memory status
- Deleting all entries
- Deleting entries by specifying week (Week View)
- Deleting entries by specifying month (1Month/3Month/6Month View)
- Deleting entries in six months (6Month View) (P.11-46)

## Information Link

Set to show or hide the following information in Calendar.

<b>Reservation List</b>	TV Timer and TV Recording Timer entries
<b>Birthday</b>	Birthdays entered in Phone Book
<b>What is today? (Japanese)</b>	Preset anniversaries, commemorative days, etc.

- 1 In Calendar window,
- 2 **Calendar Settings**  $\rightarrow$
- 3 **Data to Show**  $\rightarrow$
- 4 Select item  $\rightarrow$  (☐/☒)
- 5

## Spinguru Log Information Link

- In Spinguru Log, operation history of various functions are also displayable.

## Editing TV Timer/TV Recording Timer

- 1 In schedule list, select entry  $\rightarrow$
- 2 **Edit**  $\rightarrow$
- 3 **Edit**  $\rightarrow$

## Deleting Entries

- In 2, **Delete**  $\rightarrow$   $\rightarrow$  **Yes**  $\rightarrow$
- Timer is canceled.

## Making Birthday Calls

- 1 In schedule list, select entry  $\rightarrow$
  - 2 **Call**  $\rightarrow$   $\rightarrow$  **Select phone number**  $\rightarrow$
- Omit number selection step if only one number is saved.

## Sending Birthday Messages

- In 2, **Mail**  $\rightarrow$   $\rightarrow$  **Select number/address**  $\rightarrow$   $\rightarrow$  **Complete message**  $\rightarrow$
- Omit number/address selection step if only one number or address is saved.
  - For phone numbers, select **S! Mail** or **SMS** and press .

## Deleting Schedules

## ■ One Entry

- 1 In schedule list, select schedule  $\rightarrow$
- 2 **Delete**  $\rightarrow$   $\rightarrow$  **This Appointment**  $\rightarrow$   $\rightarrow$  **Yes**  $\rightarrow$

## ■ All Entries of the Day


- 1 In Calendar window, select date  $\rightarrow$
- 2 **Delete**  $\rightarrow$   $\rightarrow$  **All This Day**  $\rightarrow$   $\rightarrow$  **Yes**  $\rightarrow$

# Tasks

## Saving Tasks

Follow these steps to save subject, due date/time, Alarm and task details:  
(Enter Subject or Description to save entry.)

- 1 → **Tools** → → In PIM/  
Life menu, **Tasks** →



- 2 **<Add New Entry>** →

- 3 **Enter subject** →



- 4 **Enter due date/time** →



- 5 **Alarm:** →

- 6 **Alarm Time:** → → **Select time** → →

- 7 **Description:** → → **Enter task details** →

- 8 → **Saved**

### Task with No Due Date/Time

In 4, → → **From** 7

### Custom Alarm Time

In 6, **Alarm Time:** → → **Other** →

→ **Enter date/time** → → →

**From** 7

## Advanced

1

- Hiding tasks
- Editing tasks
- Setting priority
- Changing Alarm tone/video & duration
- Changing Alarm volume
- Selecting Vibration option
- Changing illumination settings
- Sounding Alarm tone even in Manner mode (P.11-46 - 11-47)

## At Alarm Time

Alarm activates; sounds/vibrates by related settings.



### Stopping Alarm to Return to Standby

- While Alarm sounds/vibrates, press or .

### Stopping Alarm to Open Task

- While Alarm sounds/vibrates, press a key other than , , or .

### When Another Function is Active

- Alarm may not activate until handset returns to Standby.

### Incoming Calls

- Active Alarm stops for incoming calls. Information window opens after handset returns to Standby.

## Opening Tasks

- ➔ **Tools** ➔ ➔ In PIM/  
Life menu, **Tasks** ➔



Task List

- Use to open Completed or Incomplete task list.

- Select task ➔



- ➔ **Standby returns**

### Accessing Secret Entries

- After
  - 
  - ➔ **Unlock Temporarily**  
➔ ➔ **Enter Handset Code** ➔

### Marking Tasks as Completed

- After
  -, select task ➔

## Deleting Tasks

### One Entry

- In task list, select task ➔

- Delete** ➔

- This Task** ➔ ➔ **Yes** ➔

### All Completed Tasks

- In task list,

- Delete** ➔

- All Comp. Tasks** ➔ ➔ **Yes** ➔

## Advanced


- Searching tasks ● Sorting tasks by priority ● Checking memory status ● Deleting all tasks (P.11-47)

## Using Alarms

### Setting Alarm


Follow these steps to set Alarm to sound at a specific time on a specific day of the week: (Set Snooze--Alarm repeats at set interval--Alarm Volume and Duration.)

- 1** **Tools** **In PIM/ Life menu, Alarms**




Alarm List

- 2** **--:--** **Enter hour (24-hour format)** **Enter minutes**



- 3** **Repeat:**



- 4** **Selected Days**

- 5** **Select day** **Complete selection**

- 6** **Snooze:**

- 7** **Select interval**   
 • For custom intervals, select *Other*.

- 8** **Alarm Volume:**

- 9** **Adjust level**

- 10** **Duration:**

- 11** **Select time**

• For custom Duration, select *Other*.

- 12** **Saved**

• For more settings, repeat **2** - **12**.

- 13** **Standby returns**

Activating Alarm Once or Daily

In **4**, **Once** or **Every Day (All)**

➔ **From** **6**

Selecting/Canceling All Days

In **5**, ➔ **Check All** or **Uncheck All**

➔

Excluding Holidays

In **5**, select day

**Complete selection** ➔ **Except**

**Holidays** ➔ ➔ **From** **6**

### Advanced

1

- Editing entries
- Saving entry name
- Changing Alarm tone/video
- Setting handset to vibrate at Alarm Time
- Changing illumination settings
- Sounding Alarm tone even in Manner mode
- Activating Alarm based on World Clock time (P.11-48)



## At Alarm Time

Alarm activates; sounds/vibrates by related settings.



### Stopping Alarm

- Press a key.

### When Another Function is Active

- Alarm may not activate until handset returns to Standby.

### Incoming Calls

- Active Alarm stops for incoming calls. Information window opens after handset returns to Standby.

## When Snooze is Set

Alarm repeats at the set interval. Other Alarms do not activate while handset is Snoozing.

### Canceling Snooze

While Snoozing, Yes

- Snooze is automatically canceled after a period of time.

## Canceling Alarm

**1** In Alarm list, select entry

**2** *Switch Off*   
• Reactivate entry to use the same settings.

### Reactivating Entry

In , *Switch On*

## Deleting Alarm

### One Entry

**1** In Alarm list, select entry

**2** *Reset Alarm*

**3** Yes

### All Entries

**1** In Alarm list, select entry

**2** *Clear All*

**3** Yes

## Using Wakeup TV

### Setting Wakeup TV

Follow these steps to activate TV at a specific time on a specific day of the week:

- Complete TV Area setup beforehand.
- TV may not activate in poor signal conditions.

**1** ➔ **Tools** ➔ ➔ **In PIM/Life menu, Wakeup TV** ➔



Wakeup TV List

**2** --:-- ➔ ➔ **Enter hour (24-hour format)** ➔ **Enter minutes** ➔



Wakeup TV Menu

- 3** **Repeat:** ➔
- 4** **Selected Days** ➔
- 5** **Select day** ➔ (/ ) ➔ **Complete selection** ➔
- 6** **Channel:** ➔
- 7** **Select channel** ➔
- 8** ➔ **Saved**
- For more settings, repeat **2** - **8**.
- 9** ➔ **Standby returns**

### Activating TV Once or Daily

In **4**, **Once or Every Day (All)** ➔ ➔ **From**

### Selecting/Canceling All Days

In , ➔ **Check All or Uncheck All** ➔

### Excluding Holidays

In , select day ➔ (/ ) ➔ **Complete selection** ➔ **Except Holidays** ➔ () ➔ ➔ **From**

### Canceling Alarm

• Alarm activates at Wakeup TV time. To cancel Alarm, follow these steps:

[Wakeup TV Menu] **Alarm On/Off:** ➔ ➔ **Off** ➔ ➔ **From**

### Adjusting Alarm Volume

[Wakeup TV Menu] **Alarm Volume:** ➔ ➔ **Adjust level** ➔ ➔ **From**

### Advanced

- Editing entries • Changing Alarm tone/video • Changing illumination settings • Sounding Alarm tone even in Manner mode (P.11-49)

## At Wakeup TV Time

TV activates after Alarm.



### Stopping Alarm Instantly

- While Alarm sounds/vibrates, press a key.

### When Another Function is Active

- TV may not activate depending on the function.

### After TV is On for a Period of Time

- A confirmation appears. Choose **Yes** and press to exit TV.

## Canceling Wakeup TV

**1** In Wakeup TV list, select entry ➔

**2** *Wakeup TV Off* ➔

- Reactivate entry to use the same settings.

### Reactivating Entry

In **2**, *Wakeup TV On* ➔

## Deleting Wakeup TV

### ■ One Entry

**1** In Wakeup TV list, select entry ➔

**2** *Reset Alarm* ➔

**3** *Yes* ➔

### ■ All Entries

**1** In Wakeup TV list, select entry ➔

**2** *Clear All* ➔

**3** *Yes* ➔

## Using Charging Theater

Play Slide Show or video while charging.

### Enabling Charging Theater

Example: Setting Slide Show  
Enabling Charging Theater sets Viewer  
Position Move Settings to *Off(Standby)*.

- 1 **Tools** In PIM/  
Life menu, **Charging  
Theater**
- 2 **Switch On/Off** **On**  
 **Yes**
- 3 **Switch Photo/Video**
- 4 **Photo** **Select sub  
folder** **Set this  
folder**

- Omit steps for sub folder when using  
images saved in Pictures folder.

### Setting Video

In 4, **Video** **Select file**

### Changing Playback Time

In 3, **Playback Time** **Select  
time**

### Enabling Video Audio Output

In 3, **Video Sound Output**   
**On**

### Disabling Repetitive Video Playback

In 3, **Video Repeat** **Once  
Play**

### Activating Charging Theater

Start charging in Standby; Slide Show or  
video plays according to settings.

### Incoming Calls while Charging Theater is Active

- Charging Theater ends.


## Playing Animation with Music & Illumination

Play preset animations or downloaded Flash® files with music and illumination. Set playback time, volume, etc. as needed.

- 1 ➔ **Tools** ➔ ➔ In PIM/Life menu, **Relaxation Time** ➔
- 2 **Select type** ➔
  - Animation appears.
  - For **Flash®**, select a file and press .
    - Key LEDs do not illuminate for soundless Flash® files.
  - Message appears when Playback Time is set to **Continuous Play** (except when charging battery); press to proceed.

### Setting Relaxation Time

Follow these steps to set playback time, volume and Key Illumination pattern:

- 1 ➔ **Tools** ➔ ➔ In PIM/Life menu, **Relaxation Time** ➔
- 2 **Settings** ➔ 

- 3 **Playback Time** ➔
- 4 **Select time** ➔
  - For custom playback time, select **Other**.
- 5 **Volume** ➔
- 6 **Adjust level** ➔
- 7 **Effect Illumination** ➔

- 8 **Key Pattern** ➔

- 9 **Select pattern** ➔ ➔

- 10 ➔ **Standby returns**

### Changing Illumination Pattern

In , **Pattern/Color** ➔ ➔ **Select pattern** ➔ ➔ **Select color** ➔ ➔

- Light color is unselectable for some patterns.

### Setting Music to Control Illumination

In , **Switch On/Off** ➔ ➔ **Link to Sound** ➔ ➔

- Key Illumination varies by music when **Link to Sound** is set.

### Disabling Illumination

In , **Switch On/Off** ➔ ➔ **Off** ➔ ➔


## Managing Household Expenses

Scan receipts with mobile camera to manage expenses on handset.

### Setup

Specify closing day, closing month and budget for the month.

- 1 → **Tools** → → **In PIM/ Life menu, Household Accounts** →



Totals Panel


Charts Panel

Manual Input Panel

Scan Receipt Panel


Household Accounts Window

- 2



Account Setup Menu

- 3 **Date/Month Closed** →



- Press to change default closing date (end of the month); use to move between date and month fields.

- 4 **Enter date/month** →

- 5 **Yes** →

- 6 **Budget** → → **Enter amount** →

- 7 → **Household Accounts window returns**

**Restricting Access to Household Accounts by Handset Code**

[Account Setup Menu] **Locks** → → **On** →

**Resetting Household Accounts**

[Account Setup Menu] **Master Reset** → → **Yes** →

## Saving Entries

## Scanning Receipts

Scan receipts with mobile camera to enter date, expense items, fees/prices and total amount automatically.

Scan may fail if receipt is too long, folded, faded, etc.; some formats are not supported.

**1 In Household Accounts window, select scan receipt panel ➡**

**2 Frame receipt on Display**



Scan Window

- Frame date, expense items and total amount. Align text parallel to reference lines.

**3**

- To cancel, press .

**4**

➡ **Scan results appear**




- To add, delete or edit expense items, see P.11-16 "Entering Manually."

**5**






- Entry is saved.

## Opening Operation Guide

[Scan Window] 

- Press  to return to scan window.

## Key Assignments in Scan Window

Toggle Focus Mode	
Focus Lock	
Mobile Light On/Off	
Adjust Brightness	
Open Help	

## Entering Manually


- 1** In Household Accounts window, select manual input panel ➡ ●



Expense Input Window

- 2** Select date panel ➡ ● ➡ Enter date ➡ ●
- 3** Shop ➡ ● ➡ Select shop/facility ➡ ●
- 4** Paid ➡ ● ➡ Select payment method ➡ ●

- 5** Item ➡ ●



- 6** Item ➡ ● ➡ Enter name ➡ ●
- 7** Category ➡ ● ➡ Select Category ➡ ●
- 8** Value ➡ ● ➡ Enter amount ➡ ● ➡ ¥
- 9** ● ➡ Saved

## Adding Expense Items

After ⑤, select item field ➡ ● ➡

Add Items ➡ ● ➡ From ⑤

## Deleting Expense Items

After ⑤, select item ➡ ● ➡ Delete

➡ ● ➡ Yes ➡ ● ➡ ⑤

## Changing Categories of All Items at Once

[Expense Input Window] Category

Change ➡ ● ➡ Select Category ➡

● ➡ ⑤

## Advanced

- Renaming icon labels ● Importing Household Accounts data ● Exporting Household Accounts data (P.11-49)



## Opening Expense Records

## Opening Entries

- 1 In Household Accounts window, select totals panel



- 2 Select date → ●

2010/7/1	
Monthly Expense	¥1,843
Daily Expense	¥1,843
スーパー 1	¥1,050
未登録店舗	¥793

Daily Expense Log

- 3 Select entry → ●

- Details appear.

## Deleting an Entry

[Daily Expense Log] Select entry → ●  
→ Delete Receipt → ● → Yes → ●

## Deleting All Entries

[Daily Expense Log] ● → Delete  
Day Data or Delete Month Data → ●  
→ Yes → ●

## Viewing Expense Trends

Follow these steps to view monthly expenses, budgets and balances:

- 1 In Household Accounts window, select charts panel



- 2 Results by Month → ●

2010		
	Balance	Expenses
Jan	¥36,110	¥203,890
Feb	¥80,000	¥180,000
Mar	¥63,000	¥177,000
Apr	¥40,300	¥199,700
May	¥80,480	¥159,520
Jun	¥57,000	¥183,000


Results by Month Window

- Press ● to toggle budget and balance.
- Use ⏮ to open previous or next year.

## Viewing Other Expense Trends

In 2, select item → ●

## Monthly Result Charts



Expenses

Balances

- In Balance chart, gray area of each bar represents balance; bar turns pink when balance is zero or less.
- In Expenses chart, orange bar extends to the left as monthly expense increases, with the middle of the chart indicating average monthly expense for the year.

## Using Calculator

- 1 ➔ **Tools** ➔ ➔ In PIM/  
Life menu, **Calculator** ➔



Calculator Window

### Key Assignments

<b>+</b> (Add)	
<b>-</b> (Subtract)	
<b>×</b> (Multiply)	
<b>÷</b> (Divide)	
<b>=</b> (Sum)	
<b>C-CE</b> (Clear)	
<b>CM</b> (Clear Memory)	
<b>RM</b> (Recall Memory)	
<b>M+</b> (Add to Memory)	
<b>.</b> (Decimal)	
<b>+/-</b> (Positive/Negative Value)	
<b>%</b> (Percentage)	

### Memory Calculation

- Clear Memory before starting new Memory calculations.
- Numbers saved in Memory remain until handset is powered off.

### Incoming Calls

- Calculations are not affected. End the call to return to Calculator.

### Using % Function

Use to find definite percentage of a known value.

Example: Calculate 30% of 800,000

Enter **800,000** ➔ **x** ➔ **30** ➔ **%**

■ **240,000** appears.

- 2 Use Keypad to enter digits  
➔ **Calculate**

- 3 ➔ **Standby returns**


### Advanced

- Copying calculation results ● Changing exchange rate for currency conversion ● Converting currencies (P.11-50)

## Adding Expenses

### Entering Expenses

- 1



Expenses Memo Menu

- 2 Select list
- 3 Add New
- 4 Enter amount



- 5 Select Category
- Saved

### Saving under Custom Category

- In , Other
- Renaming Lists**  
 [Expenses Memo Menu] Select list
- Resetting All List Names**  
 [Expenses Memo Menu]

### Checking Entries

- 1 In Expenses Memo menu, select list



Expenses Memo List

- 2

### Saving Entries to Notepad

- [Expenses Memo List] Select entry

### Deleting Entries

#### ■ One Entry

- 1 In Expenses Memo list, select entry
- 2 Delete Item
- 3 Yes

#### ■ All Entries

- 1 In Expenses Memo list, select entry
  - 2 Delete All
  - 3 Yes
- All entries on the list are deleted.

### Advanced

- Changing Category of saved entry Changing amount Renaming Categories (P.11-50)

## Osaifu-Keitai® (Japanese)

Osaifu-Keitai® describes IC Card-equipped handsets that support e-money or credit functions/services. Osaifu-Keitai® encompasses a range of IC Card-based services on FeliCa-compatible SoftBank handsets. 945SH supports Osaifu-Keitai®. To use e-money, e-ticketing and reward points, etc., hold handset over a compatible reader/writer at shops, restaurants, and other retail outlets, etc.

### Basics

Before using Osaifu-Keitai®, activate Lifestyle-Appli, complete registration, customize settings and charge accounts.

#### Starting Lifestyle-Appli

● ➔ **Tools** ➔ ● ➔ In PIM/Life menu,  
**Osaifu-Keitai** ➔ ● ➔ **Lifestyle-Appli**  
➔ ● ➔ **Select application** ➔ ●

#### Important Lifestyle-Appli Usage Notes

- Contact Osaifu-Keitai® service providers for Lifestyle-Appli registration and usage details.
- Keep service passwords/customer service contact information, etc. in a separate place.


### Using Osaifu-Keitai®

Follow these steps to conduct a transaction:

Example: Making an electronic payment

- Lifestyle-Appli activation is not necessary.
- Transactions are possible even while handset is off (if battery is adequately charged).
- Calls/Internet transmissions do not affect transactions.

**1** Place  logo over reader/writer ➔ **Confirm scan results**



Place this part  
over reader/writer

- Align handset parallel to reader/writer.

### Important Osaifu-Keitai® Usage Note

- SoftBank Mobile is not liable for damages resulting from accidental loss/alteration of IC Card data/settings.

#### When Placed Over Sensor

- If recognition is slow, move handset around slightly.
- Handset may respond automatically for some services.

### Advanced

-  ● Enabling to view e-money balances ● Moving applications up/down Balance Info list ● Removing applications from Balance Info list (P.11-50)

# Locking IC Card


## IC Card Lock

Restrict access to/prevent unauthorized use of Osaifu-Keitai® on handset.

- 1 **Tools** **In PIM/**  
**Life menu, Osaifu-Keitai**



- 2 **IC Card Settings**



IC Card Settings Menu

- 3 **IC Card Lock** **On**

- 4 **Yes**

### Canceling IC Card Lock

- In , **IC Card Lock** **Off**

- Enter Handset Code**

## Advanced

- Customizing handset response to reader/writer commands Opening IC Card properties Changing IC Card Lock notice recipient Changing required Missed Call count for Call Remote Lock Restoring default Osaifu-Keitai® settings (P.11-50 - 11-51)

## Remote Lock

Disable Osaifu-Keitai® remotely by mail or phone.


<b>Mail Remote Lock</b>	Send mail to activate Remote Lock
<b>Call Remote Lock</b>	Call from a specified phone to activate Remote Lock

### Mail Remote Lock

#### ■ Preparation on Handset

- 1 ● ➔ **Tools** ➔ ● ➔ In PIM/Life menu, **Osaifu-Keitai** ➔ ●
- 2 **IC Card Settings** ➔ ●
- 3 **Remote Lock** ➔ ● ➔ Enter Handset Code ➔ ●

#### 4 Mail Remote Lock ➔ ●



Mail Remote Lock Menu

#### 5 Remote Lock PW ➔ ●

#### 6 Enter password ➔ ●

#### 7 Switch On/Off ➔ ●

#### 8 On ➔ ● ➔ ●

#### Canceling Mail Remote Lock

In ●, **Switch On/Off** ➔ ● ➔ **Off** ➔ ● ➔ ●

#### ■ Activating Remote Lock via Mail

If handset cannot receive mail, IC Card Lock remains unset.


#### 1 Send S! Mail or e-mail to handset with password as subject

- After handset receives message, IC Card Lock is set and notice is sent as a reply.

## Call Remote Lock


### ■ Preparation on Handset

- 1 ➔ **Tools** ➔ ➔ **In PIM/ Life menu, Osaifu-Keitai** ➔
- 2 **IC Card Settings** ➔
- 3 **Remote Lock** ➔ ➔ **Enter Handset Code** ➔
- 4 **Call Remote Lock** ➔



Call Remote Lock Menu

- 5 **Phone No. to Lck 1 or Phone No. to Lck 2** ➔



- 6 **Phone Book** ➔ ➔ **Select entry** ➔ ➔ **Select phone number** ➔
- Select *Phone Number* to enter directly.

- 7 **Switch On/Off** ➔

- 8 **On** ➔ ➔

### Enabling Activation via Public Phone

In 5, **Set Public Phone** ➔ ➔ **On** ➔ ➔ **From**

### Canceling Call Remote Lock

In 5, **Switch On/Off** ➔ ➔ **Off** ➔ ➔

### ■ Activating Remote Lock via Phone

If handset cannot receive calls, IC Card Lock remains unset.

- 1 **Using one of the specified phones, call handset**

- Send Caller ID.

- 2 **Handset receives call** ➔ **End the call**

- The call is recorded as a Missed Call.

- 3 **Within three minutes, repeat 1 - 2 twice**

- After the third Missed Call, IC Card Lock is set; a message announces Remote Lock activation. Confirm the message and end the call.

### If Series is Interrupted by Another Call

- Missed Call count is reset. Start over from the beginning.


## Faking Incoming Calls

Handset rings to emulate an incoming call.

- Save name and phone number to show as Caller ID.
- Ringer may be muted by handset settings. To override Silent setting, see P.11-51.

### Setting Simulated Call

- 1 → **Tools** → → In PIM/Life menu, **Simulated Call** →



Simulated Call Menu

- 2 **Switch On/Off** → → **On** →

- 3 **Set Caller** →
- 4 **Name:** → → Enter name →
- 5 **Phone Number:** → → Enter phone number → →
- 6 **Assign Tone** → → Select tone/file →
- 7 → PIM/Life menu returns

When Name and Phone Number are Unset

- Handset rings with Caller ID "Withheld."

**Canceling Simulated Call**

[Simulated Call Menu] **Switch On/Off**

→ → **Off** → →

**Setting Wait Time**

[Simulated Call Menu] **Receive Timing**

→ → Select time → →

### Using Simulated Call

- 1 (Long)
  - Handset rings and incoming Voice Call window opens.
  - Ringtone stops after a period of time.
- 2 In incoming Voice Call window, press
  - Voice Call window opens. (Softkeys are dummies.)
- 3 → Standby returns

When Receive Timing is Not Immediately

- Press or during wait time to cancel Simulated Call activation.
- Simulated Call activation is canceled by incoming calls, Alarms, etc. during wait time.

### Advanced


- Starting via Simulated Call menu
- Clearing caller information
- Overriding Silent volume setting (P.11-51)



## Using Stopwatch

Stopwatch stops if battery runs low.

- 1** ➔ **Tools** ➔ ➔ ➔ **Clock/Gauge** ➔ **Stopwatch** ➔



Stopwatch Window

- 2** ➔ **Stopwatch starts**
- 3** ➔ **Stopwatch stops**  
 • Press to resume.
- 4** ➔ **Yes** ➔ ➔ **Stopwatch ends**  
 • Records are deleted when Stopwatch ends.

### Recording Lap Times

While Stopwatch is running,

### Saving Records to Notepad

After , ➔ **Save to Notepad** ➔

### Resetting Records


After , ➔ **From**

### Incoming Calls

- Stopwatch is not affected by incoming calls. End the call to return.

## Using Countdown Timer

- 1**
- Tools** **Clock/Gauge** **Countdown Timer**



Timer Entry Window

- 2** Enter minutes Enter seconds

- Tap **+10min**, **+1min** or **+30sec** as needed.

- 3**



Countdown Timer Window

- Press to change time.

- 4** **Countdown starts**

- Press to stop/resume countdown.

- 5** Set time elapses **Tone sounds**

- 6**
- Countdown Timer ends**

### Using Timer Records

After **1**, **Input History**

Select record **From** **4**

### Resetting Countdown Timer


Stop countdown and

### Incoming Calls

- Countdown is not affected by incoming calls. End the call to return.

### When Set Time Elapses

Tone sounds.



### Stopping Tone Instantly

- Press or . (Tone stops automatically after a period of time.)

### When Timer Time Elapsed during a Call

- Tone sounds after the call.

### Advanced

- Changing illumination settings (P.11-51)

## Opening World Clock


- 1 ➔ **Tools** ➔ ➔ ➔ **Clock/Gauge** ➔ **World Clock** ➔



Local Time  
Zone

World Time  
Zone

- 2



Set Time Zone Window

- 3 **Select area** ➔

- 4 ➔ **Standby returns**

**Advancing One Hour (Daylight Saving)**

[Set Time Zone Window]

■ To cancel, press .

**Adding Custom Time Zone**

[Set Time Zone Window] ➔ Enter

city name ➔ ➔ + or - ➔ ➔

Enter time difference ➔

### Opening World Clock in Standby

- 1 ➔ **Settings** ➔ ➔ In  
Sound/Display menu,  
**Display** ➔

- 2 **Standby Display** ➔

- 3 **Clock/Calendar** ➔

- 4 **World Clock (L), etc.** ➔

- 5 ➔ **Standby returns**

## Using Hour Minder

### Setting Hour Minder

Follow these steps to activate the hourly time signal at selected hours:

- 1 → **Tools** → → **Clock/Gauge** → **Hour Minder** →



Hour Minder Menu

- 2 **Switch On/Off** → → **On** →

- 3 **Select Time** →



- 4 **Select hour** → → → **Complete selection** →

- 5 → **Saved**

- 6 → **Standby returns**

#### Adjusting Hour Minder Volume

In 2, **Advanced** → → **Volume:** → → **Adjust level** → → → **From**

#### Changing Hour Minder Duration

In 2, **Advanced** → → **Duration:** → → **Select time** → → → **From**


■ For custom Duration, select **Other**.

#### Selecting/Canceling All Hours

In 4, → **Check All** or **Uncheck All** →

### At Hour Minder Time

Hour Minder activates; sounds/vibrates by related settings.



#### Stopping Tone Instantly

- Press a key.

#### When Another Function is Active

- Hour Minder does not activate.
- **Incoming Calls**
- Active Hour Minder stops for incoming calls.

### Canceling Hour Minder

- 1 In Hour Minder menu, **Switch On/Off** → → **Off** → →

### Advanced

- Changing Hour Minder tone/video
- Setting handset to vibrate at Hour Minder Time
- Changing illumination settings
- Sounding Hour Minder tone even in Manner mode
- Activating Hour Minder based on World Clock time (P.11-52)

# Using Pedometer

## Getting Started

- Count based on a pace of approximately 100 steps per minute over even terrain.
- Accuracy may be affected by course, terrain, walking style, etc.
- Avoid holding the handset; use a body worn case or a strap, or place handset inside a pocket or bag.
  - Avoid sudden/erratic movements.
- Steps are not counted in the following cases:
  - While handset is off
  - For the first few steps
  - While handset vibrates
- Handset use may affect accuracy.
- Weight and pace entry required to view full Pedometer data.
- Use Pedometer only as a rough guide.

## Adjusting Counter Sensitivity

- ➔ **Tools** ➔ ● ➔ ● ➔ **Clock/Gauge** ➔ **Pedometer** ➔ ● ➔ ● ➔ **Settings** ➔ ● ➔ **Step Sensitivity** ➔ ● ➔ **Select option** ➔ ●
- Select **Low** when steps seem overcounted; select **High** when they seem undercounted.

## Saving Body Information

- 1 ● ➔ **Tools** ➔ ● ➔ ● ➔ **Clock/Gauge** ➔ **Pedometer** ➔ ● ➔ ●



Pedometer Window

- If Pedometer is disabled, a confirmation appears. Choose **Yes** or **No** and press ●.

- 2 ● ➔ **Settings** ➔ ● ➔ ● ➔ **Body Info.** ➔ ●



Body Info Menu

- 3 **Height** ➔ ● ➔ Enter height ➔ ●

- 4 **Weight** ➔ ● ➔ Enter weight ➔ ●

- 5 **Pace** ➔ ● ➔ **Yes or No** ➔ ●
  - Choose **Yes** to enter pace automatically based on height.

- 6 Enter pace ➔ ● ➔ ●

## Editing Body Information

- [Body Info Menu] Select item ➔ ● ➔ Enter value ➔ ● ➔ ●
- For **Pace**, automatic calculation confirmation appears (when height is entered).

## Enabling Pedometer

- 1 In Pedometer window, ● ➔ **Pedometer On** ➔ ●

## Disabling Pedometer

- [Pedometer Window] ● ➔ **Pedometer Off** ➔ ●

## Viewing Step Count Records

## 1 In Pedometer window,



Steps Window

- Press to toggle Daily/Hourly view.
- Press or to scroll down or up by one page.

## 2 Select time/date

- Hourly/daily step counts appear.

## 3 returns

## Pedometer Window Tabs

- Press to open Exercise and then Calories.

## Resetting Today's Step Count

[Pedometer Window]

Day's Data

## Resetting Log

[Steps Window]

Reset

- Today's data is also reset.

## Setting Targets

Information window opens, etc. when target is achieved for these items:

Steps	Walking Time
Exercise	Calories
Distance	Fat burned

## 1 In Pedometer window,

## 2 Target Settings

## 3 Select item Enter value/time

- Other target settings may consequently change.

## Editing Targets

[Pedometer Window]

Settings

## When Target is Achieved

- A tone sounds and Information window opens. (Select **Goal Achievement** and press to open Pedometer Calendar.) Follow these steps to mute achievement tone:

[Pedometer Window]

Announce

## About Exercise (Ex)

- Ex and MET indicate amount and intensity of physical activity, respectively. Ex for walking is calculated by multiplying 3 METs by walking duration (hour).

## Advanced

- Using Pedometer Calendar Checking accumulated data Resetting accumulated data Setting daily step count reset time Customizing achievement notice (P.11-52 - 11-53)

# Using Compass

## Opening Compass

- 1 ● ➔ *Tools* ➔ ● ➔ ●  
*Clock/Gauge* ➔ *Compass*  
 ➔ ●



Compass Window

- Compass opens; use as a rough guide.

## Adjusting Compass

- 1 In Compass window, ● ➔ ●  
 • Follow onscreen instructions.

### Compass Indicator

- When map is open, compass indicator appears; follow these steps to hide it:  
 ● ➔ *Tools* ➔ ● ➔ ● *Clock/Gauge*  
 ➔ *S! GPS Navi* ➔ ● ➔ *NAVI*  
*Settings* ➔ ● ➔ *Compass Indicator*  
 ➔ ● ➔ *Off* ➔ ●

## Using S! GPS Navi

Use this GPS navigation service to pinpoint current location, find routes to destinations, and more.

- Provide current location to administrator upon request.
- Available in clamshell open or Viewer position.

### Precautions

- Location Information accuracy may be affected when GPS satellite/radio station signal reception is poor. Use S! GPS Navi under the open sky.
- SoftBank Mobile is not liable for any damages resulting from the provided Location Information.

### Positioning

- Pinpoints current location using signals transmitted from GPS satellites.


### Location Information Accuracy

- Probable distance from the actual position is classified into three accuracy levels, from level 1 (low) to 3 (high), indicated by the number of 📶s.
- A confirmation appears when accuracy level is 1 or 2; follow these steps:

**Yes or No ➡** ●

### Starting Navi-Appli

- 1** ● ➡ **Tools** ➡ ● ➡ ● ➡ **Clock/Gauge** ➡ **S! GPS Navi** ➡ ●



S! GPS Navi Menu

- 2** **Navi Appli** ➡ ●
- To disable confirmation, press ☹ before ☺.

- 3** **Yes** ➡ ●

### Opening Navi Appli List

[S! GPS Navi Menu] **Navi Appli List** ➡ ●


- To activate Navi Appli, select one and press ●.

### Selecting a Navi-Appli for S! GPS Navi

[S! GPS Navi Menu] **NAVI Settings** ➡ ● ➡ **Select Navi Appli** ➡ ● ➡ **Select application** ➡ ●




## Opening Location Log

- 1 In S! GPS Navi menu, **Location Logs** ➡ ●
- 2 **Select record** ➡ ●
  - Details appear.
- 3  ➡ **List returns**

## Pinpointing Current Location

- 1 In S! GPS Navi menu, **Locate Me** ➡ ●




- To disable confirmation, press  before 2.
- 2 **Yes** ➡ ● ➡ **Positioning starts**
    - Map of your current location appears.

## Using My Location


## Saving Location Information

Follow these steps to save current location as a new entry:


- 1 In S! GPS Navi menu, **My Location List** ➡ ●



My LocationList Menu

- 2 **New Entry** ➡ ●
- 3 **Name** ➡ ● ➡ **Enter name** ➡ ●
- 4 **Location Info** ➡ ●
- 5 **From Current Loc.** ➡ ● ➡ **Positioning complete**
- 6 ●
  - When accuracy level is 1 or 2, choose **No** and press ● to proceed to 7.
- 7 

## Saving as Home

In 2, **自宅** ➡ ● ➡ **From** 4  
**Saving from Location Log**  
 In 5, **From Location Logs** ➡ ● ➡  
**Select record** ➡ ● ➡ 

## Opening Entries

- 1 In My LocationList menu, **select entry** ➡ ●
- 2 **Location Info** ➡ ●
  - Details window opens.
- 3  ➡ **Details window closes**

## Deleting Entries

- 1 In My LocationList menu, **select entry**
- 2  ➡ **Delete** ➡ ● ➡ **Yes** ➡ ●

## Advanced

-  ● Sending current location via mail ● Changing map source URL ● Disabling positioning ● Selecting Location Information transmission option ● Using My Location & Location Log ● Saving Location Log records to My Location ● Deleting Location Log records (P.11-53)

## Using Ichi Navi (Japanese)

Locate other S! GPS Navi-compatible handset users or lost handset.

- Ichi Navi requires a separate contract and initial settings.
- If Double Number is active, service uses Line A regardless of usage mode setting.
- For more about Ichi Navi, see SoftBank Mobile Website (P.17-24).

### 1 In S! GPS Navi menu, *Location Navi* ➡ ●

- Handset connects to the Internet.  
Follow onscreen instructions.

## Providing Location Information

Provide current location to administrator upon request.

- Location may be provided automatically upon administrator's request without confirmation.
- May be unavailable depending on subscription. For details, contact the nearest SoftBank Shop or SoftBank Mobile Customer Center, General Information (P.17-43).

### 1 Location Information request arrives



- A confirmation appears. (Message shown above is for reference only.)

### 2 (provide) or (reject)

## Information

Information window opens after your location is provided manually (by pressing (provide)) upon Location Information request or automatically upon administrator's request. Select the item and press (confirm) to open log.

## Advanced

- Suppressing Information window after sending Location Information automatically (P.11-54)

## Opening PC Documents

Supported File Formats:

PDF (.pdf)
Microsoft® Excel® (.xls)
Microsoft® Word (.doc)
Microsoft® PowerPoint® (.ppt)

- Some files may not appear correctly.
- Downloaded files are also supported.
- When transferring files from PCs, save to corresponding Memory Card folder (P.17-25).

**1** ➔ **Tools** ➔ ➔ **Doc./Rec.** ➔ **Document Viewer** ➔

**2** **Select file** ➔

**Zooming In/Out with Loupe (Magnifier)**

In open file, (Long) ➔ **Specify portion** ➔ ➔ **Zoom Out or Zoom In** ➔


### Key Assignments

View Whole Page	
Scroll	
View Upper Left	
Toggle Full Screen View On/Off	
View Upper Right	
Zoom Out	
Continuous Zoom Out	(Long)
View Center	
Zoom In	
Continuous Zoom In	(Long)
View Lower Left	
Jump to Page	
View Lower Right	
Open Help	
Next Page	
Previous Page	
Fit Width	
Rotate 90 Degrees	

## Saving Text

### New Notepad Entry

- 1 ➔ **Tools** ➔ ➔ ➔ **Notepad** ➔



Notepad List

- 2 **<Add New Entry>** ➔
- 3 **Enter text** ➔
- 4 **Select Category** ➔ ➔ ➔ **Saved**

### Sorting Entries Temporarily

[Notepad List]

- Press to toggle sort options (Modified, Created, Category and Accessed).

### Changing Landscape Notepad List View

- [Notepad List] **Select entry** ➔ ➔ **Setting/Manage** ➔ ➔ **Landscape Display** ➔ ➔ **Select option** ➔

### Inserting Notepad Text during Text Entry

- [Text Entry Window] ➔ **Notepad** ➔ ➔ **Call Notepad** ➔ ➔ **Select entry** ➔

- Not available in Notepad text entry window.

### Opening Notepad

- 1 In Notepad list, select entry ➔
  - Text appears.
- 2 ➔ **List returns**

### Deleting Entries

#### One Entry

- 1 In Notepad list, select entry ➔

- 2 **Delete Item** ➔ ➔ **Yes** ➔

#### Selected Entries

- 1 In Notepad list, select entry ➔ ➔ **Setting/Manage** ➔

- 2 **Multiple Selection** ➔ ➔ **Select entry** ➔ ( ☐ / ☒ ) ➔ **Complete selection** ➔

- 3 **Delete** ➔ ➔ **Yes** ➔

### Unchecking All

- In , **Uncheck All** ➔

#### All Entries

- 1 In Notepad list, select entry ➔ ➔ **Setting/Manage** ➔

- 2 **Delete All** ➔ ➔ **Yes** ➔

### Advanced

- Editing Notepad
- Searching text within all entries
- Inserting Notepad text into message text
- Sending entries via S! Mail
- Creating text files
- Importing text files
- Checking memory status
- Opening properties (P.11-54)

## Using ASCII Art

### Inserting ASCII Art

- 1 In message text entry window, ➔ **Call ASCII Art** ➔

- 2 Select entry ➔



### Previewing ASCII Art

- In , select entry ➔
- Press to insert ASCII Art.

### Editing Entries

- 1 ➔ **Tools** ➔ ➔ ➔ **Doc./Rec.** ➔ **ASCII Art** ➔



ASCII Art List

- 2 Select entry ➔ ➔ **Edit** ➔

### Opening Entries

- In , select entry ➔ ➔ **View** ➔

### Adding New Entries

- In , <Empty> ➔ ➔ **Create ASCII Art** ➔

### Deleting Entries

- 1 In ASCII Art list, select entry ➔ ➔ **Delete** ➔


- 2 Yes ➔

## Recording/Playing Voice

### Recording

- Recording stops if battery runs low while recording.
- Record conversations during calls via **Record Caller Voice**.


1 → **Tools** → → **Voice Recorder** →



Recording Window

2 → **Recording starts**

3 → **Recording ends**



- For **Extended Voice**, recording is saved automatically.

4 **Save** →

**Play Before Saving**  
 In 4, **Playback** → → **Playback starts** → → **Playback stops**  
**Starting Over**  
 In 4, → **From** 2

### Playback

1 In recording window, → **Ring Songs-Tones** →

2 **Select file** →

**Playing Files via Data Folder**  
 → **Data Folder** → → **Ring Songs-Tones** → → **Select file** →

### Playback Operations


Volume Control	
Pause/Resume	
Stop	

## Scanning Barcodes

Scan UPC/JAN (1D barcodes) or QR Codes (2D barcodes).


Some barcodes may not be scanned.

- 1** ● ➔ **Tools** ➔ ● ➔ ● ➔ **Doc./Rec.** ➔ **Barcode/Scan** ➔ ●



- 2** **Scan Barcode** ➔ ●

- 3** **Frame barcode in center of Display**




Scan Window

- Use Focus Adjustment Bar as a guide (better focus in darker blue).

- 4** ● ➔ **Scan starts**

- If recognition takes time, slowly adjust the distance between handset and barcode.
- To cancel, press ⏏.

- 5** **Tone sounds ➔ Scan results appear**



### Split Data

- After scanning, a confirmation appears. Follow onscreen prompt(s).
- Scan results do not appear until all split data is scanned.

### Starting Over

After ⏏, ⏏ ➔ Yes ➔ ● ➔ From 3

### Key Assignments in Scan Window

Toggle Focus Mode	3
Switch to Photo Camera	7
Focus Lock	⏏
Mobile Light On/Off	#
Adjust Brightness	⏏
Open Help	0

### Advanced

- Scanning during text entry ● Scanning continuously ● Reading saved barcode images ● Saving scan results ● Saving to Notepad ● Saving linked info to Phone Book ● Opening saved scan results ● Using linked info ● Using images as Wallpaper ● Saving images & melodies ● Copying text (And more on P.11-55 - 11-56)

## Creating QR Codes

Create QR Codes from these items on handset:

Phone Book	My Details
Text Input	Ring Songs/Tones
Pictures	Notepad

Large items are divided into multiple QR Codes.

### Procedure

Follow these steps to create QR Codes from Data Folder files:

- 1 → **Tools** → → **Doc./Rec.** → → **Barcode/Scan** →
- 2 **Create QR Code** →
- 3 **Data Folder** →
- 4 **Select folder** → → **Select file or entry** →
  - QR Code is created.
- 5
  - QR Code is saved to Data Folder (Pictures).

### From Phone Book Entries

In , **Phone Book** → → **Select entry** → →

### From My Details

In , **My Details** → → →

### From Entered Text

In , **Text Input** → → **Enter text** → →

### Switching Storage Media

In , → **Save to** → → **Phone or Memory Card** → →

### Attaching to S! Mail

In , → **Send As Message** → → **Complete message** →

### Incoming Calls

• QR Code creation is not affected by incoming calls. End the call to return.



## Scanning Business Cards

Scan business cards and save names, addresses, etc. to Phone Book.

- English business cards may not be scanned correctly.
- Some cards may not be scanned.

**1** ● ➔ **Tools** ➔ ● ➔ ● ➔ **Doc./Rec.** ➔ **Barcode/Scan** ➔ ●

**2** **Scan Card** ➔ ●


**3** **Frame card on Display**



Scan Window

**4** ●  
● To cancel, press **Y**.

**5** ● ➔ **Scan results appear**



**6** ● ➔ **Y**  
● New Phone Book entry is saved.

### If Text Exceeds Phone Book Entry Item Character Limit

- A confirmation appears. Follow these steps to delete overage:

**Yes** ➔ ●

### Switching Storage Media

After **5**, **Q** ➔ **Save to** ➔ ● ➔ ●

**Select storage media** ➔ ● ➔ ●

### Saving Scanned Image as Phone Book Picture

After **5**, **Q** ➔ **Add Image** ➔ ● ➔ ●

**On** ➔ ● ➔ **5**

### Starting Over

After **5**, **Y** ➔ **Yes** ➔ ● ➔ **From** **3**

### Key Assignments in Scan Window

Toggle Focus Mode	<b>3</b>
Switch to Photo Camera	<b>7</b>
Focus Lock	
Mobile Light On/Off	<b>#</b>
Adjust Brightness	
Open Help	<b>0</b>

### Advanced

- Saving to Notepad ● Pasting to message text ● Copying text (P.11-57)

## Scanning Text

Scan text and save it to Notepad, etc.

Available Modes:

Full	Capture text in full screen and scan a selected line
Line	Capture a few lines of text and scan a selected line


- To toggle mode, press in scan window.
- Some text may not be scanned.

**1** ➔ **Tools** ➔ ➔ ➔

**2** **Scan Text** ➔

- To change mode, press in scan window.

**3** **Frame text in center of Display**




Scan Window

**4** ➔ **Scan starts**

- To cancel, press .

**5** **Select line** ➔ ➔ **Scan results appear**

**6**



**7** ➔ **Notepad** ➔

### Correcting Text Type

After , ➔ **Change Mode** ➔

➔ **Select type** ➔ ➔ From

### Editing Scanned Text

After , ➔ **Select/Edit** ➔

Select character ➔ Select alternative from list or edit directly ➔ From

### Starting Over

In , ➔ **Yes** ➔ ➔ From

### Key Assignments in Scan Window

Toggle Focus Mode	
Switch to Photo Camera	
Focus Lock	
Mobile Light On/Off	
Adjust Brightness	
Open Help	

### Advanced

1

- Scanning and pasting during text entry
- Scanning more text
- Saving scan results
- Saving linked info to Phone Book
- Opening saved scan results
- Using linked info
- Pasting to message text
- Copying text (P.11-57 - 11-58)

# Using Kanji/English Grabber


Scan a kanji compound or English word and look it up in dictionaries.

Some kanji/English words may not be scanned.

1 ● ➔ **Tools** ➔ ● ➔ ●  
**Doc./Rec.** ➔ **Barcode/Scan**  
 ➔ ●

2 **Kanji/English Grabber** ➔ ●

3 **Frame word in Loupe**



Loupe

Scan Window

4 ●

- Scanned word appears with reading (for kanji) or meaning (for English).

5 ●

- If there is only one search result, definition/translation window opens; omit ⑤.

6 **Select word, etc.** ➔ ●

- Definition/translation window opens.

## Starting Over

In ⑤, ⑦ ➔ From ⑤

## Key Assignments in Scan Window

Toggle Focus Mode	③
Switch to Photo Camera	⑦
Focus Lock	⌂
Zoom In/Out	⬇️⬆️⬆️⬆️
Mobile Light On/Off	⌘
Adjust Brightness	⬆️⬇️⬆️⬆️
Open Help	0

## Advanced

- Scanning and pasting during text entry (P.11-58)

## Calendar

### View Settings

Changing default view	<p>● → <b>Tools</b> → ● → In PIM/Life menu, <b>Calendar</b> → ● → <b>Calendar Settings</b> → ● → <b>Default View</b> → ● → <b>Select type</b> → ●</p>
Jumping to specified date	<p>● → <b>Tools</b> → ● → In PIM/Life menu, <b>Calendar</b> → ● → <b>8</b> → Enter date → ●</p>
Changing date color	<p><b>Start Here</b> ● → <b>Tools</b> → ● → In PIM/Life menu, <b>Calendar</b> → ● → See below</p> <p><b>By Days of the Week</b></p> <p>☰ → <b>Calendar Settings</b> → ● → <b>Set Color</b> → ● → <b>By Week</b> → ● → <b>Select day</b> → ● → <b>Select color</b> → ●</p> <p><b>By Date</b></p> <p>Select date → <b>4</b> → <b>Select color</b> → ●</p> <p>• Not available in 6Month View.</p> <p><b>Resetting "By Date" Colors</b></p> <p>☰ → <b>Calendar Settings</b> → ● → <b>Set Color</b> → ● → <b>Reset Color</b> → ● → <b>Select option</b> → ● → <b>Yes</b> → ●</p>
Selecting task view option	<p>● → <b>Tools</b> → ● → In PIM/Life menu, <b>Calendar</b> → ● → ☰ → <b>Calendar Settings</b> → ● → <b>Tasks View</b> → ● → <b>Select option</b> → ●</p>
Adding stamps (1Month/3Month View)	<p>● → <b>Tools</b> → ● → In PIM/Life menu, <b>Calendar</b> → ● → <b>Select date</b> → <b>2</b> → <b>Select stamp</b> → ●</p>
Hiding schedules	<p>● → <b>Tools</b> → ● → In PIM/Life menu, <b>Calendar</b> → ● → <b>Select date</b> → ● → <b>Select entry</b> → ● → <b>Secret:</b> → ● → <b>On</b> → ● → <b>Y</b></p>

### Saving additional holidays

**Start Here** ● → **Tools** → ● → In PIM/Life menu, **Calendar** → ● → ☰ → **Calendar Settings** → ● → **Set Holiday** → ● → **Private** → See below

#### Adding Holidays

<Empty> → ● → Enter name → ● → Enter date → ● → **Select frequency** → ● → **Y**

#### Editing Added Holidays

Select holiday → ☰ → **Edit** → ● → **Name:** → ● → Enter name → ● → **Date:** → ● → Enter date → ● → **Select frequency** → ● → **Y**

### Hiding/showing holidays

● → **Tools** → ● → In PIM/Life menu, **Calendar** → ● → ☰ → **Calendar Settings** → ● → **Set Holiday** → ● → **Private or Public** → **Select holiday** → ● (☐/☑)

### Saving/Editing Schedules

#### Setting Location

● → **Tools** → ● → In PIM/Life menu, **Calendar** → ● → **Select date** → ● → **Select entry** → ● → **Location:** → ● → Enter location → ● → **Y**

#### Creating Categories

**Start Here** ● → **Tools** → ● → In PIM/Life menu, **Calendar** → ● → ☰ → **Calendar Settings** → ● → **Set Category** → ● → See below

#### Renaming Categories

Select Category → ● → **Edit Category Name** → ● → Enter name → ●

#### Changing Icons

Select Category → ● → **Change Icon** → ● → **Select Pictogram** → ●

#### Resetting

☰ → **Reset Settings** → ● → **Yes** → ●

Saving repetitive schedules	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <i>Calendar</i> ➔ ● ➔ Select date ➔ ● ➔ Select entry ➔ ● ➔ <b>Repeat:</b> ➔ ● ➔ Select frequency ➔ ● ➔ Enter repeat time ➔ ● ➔ </p> <p>• Repeat time is not available for <i>Every Year</i>.</p>
Saving S! Friend's Status information	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <i>Calendar</i> ➔ ● ➔ Select date ➔ ● ➔ Select entry ➔ ● ➔ <b>S! Friend's Status:</b> ➔ ● ➔ <b>Link Setting:</b> ➔ ● ➔ <b>Linked</b> ➔ ● ➔ See below</p> <p><b>Availability</b>  <b>Answer Status:</b> ➔ ● ➔ Edit ➔  ➔  ➔ </p> <p>• Set Category first.</p> <p><b>Comment</b>  <b>Comment:</b> ➔ ● ➔ Enter text ➔ ● ➔  ➔ </p> <p>• Set Category first.</p>
Editing entries	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <i>Calendar</i> ➔ ● ➔ Select date ➔ ● ➔ Select entry ➔ ● ➔ Select item ➔ ● ➔ Edit in the same manner as saving schedules ➔ </p>
Changing Alarm tone/video & duration	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <i>Calendar</i> ➔ ● ➔ Select date ➔ ● ➔ Select entry ➔ ● ➔ <b>Alarm:</b> ➔ ● ➔ See below</p> <p><b>Alarm Tone/Video</b>  <b>Assign Tone/Video:</b> ➔ ● ➔ Select folder ➔ ● ➔ Select tone/file ➔ ● ➔  ➔ </p> <p>• Select start point if required.</p> <p><b>Duration</b>  <b>Duration:</b> ➔ ● ➔ Select time ➔ ● ➔  ➔ </p> <p>• For custom Duration, select <b>Other</b> and press ●.</p>

Changing Alarm volume	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <i>Calendar</i> ➔ ● ➔  ➔ <b>Alarm Settings</b> ➔ ● ➔ <b>Alarm Volume:</b> ➔ ● ➔ Adjust level ➔ ● ➔</p>
Selecting Vibration option	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <i>Calendar</i> ➔ ● ➔  ➔ <b>Alarm Settings</b> ➔ ● ➔ <b>Vibration:</b> ➔ ● ➔ Select option ➔ ● ➔</p>
Changing illumination settings	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <i>Calendar</i> ➔ ● ➔  ➔ <b>Alarm Settings</b> ➔ ● ➔ <b>Effect Illumination:</b> ➔ ● ➔ See below</p> <p><b>Setting Alarm Tone to Control Illumination</b>  <b>Switch On/Off</b> ➔ ● ➔ <b>Link to Sound</b> ➔ ● ➔ </p> <p><b>Changing Illumination Pattern</b>  <b>Pattern/Color</b> ➔ ● ➔ Select pattern ➔ ● ➔ Select color ➔ ● ➔ </p> <p>• Light color is unselectable for some patterns.</p> <p><b>Changing Key Illumination Pattern</b>  <b>Key Pattern</b> ➔ ● ➔ Select pattern ➔ ● ➔ </p> <p>• Regardless of Key Pattern setting, ringtones control illumination when Switch On/Off is set to <b>Link to Sound</b>.</p> <p><b>Disabling Illumination</b>  <b>Switch On/Off</b> ➔ ● ➔ <b>Off</b> ➔ ● ➔ </p>
Sounding Alarm tone even in Manner mode	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <i>Calendar</i> ➔ ● ➔  ➔ <b>Alarm Settings</b> ➔ ● ➔ <b>For Manner Mode:</b> ➔ ● ➔ <b>Ring</b> ➔ ● ➔ <b>Yes</b> ➔ ● ➔</p>

## Managing Schedules

Searching entries	<p>[Start Here] → Tools → In PIM/Life menu, <i>Calendar</i> → See below</p> <p><b>By Part of Subject</b></p> <p>6 → Enter text →</p>
	<p><b>By Category</b></p> <p>9 → Select Category →</p>
Checking memory status	<p>Tools → In PIM/Life menu, <i>Calendar</i> → Select date → <i>Memory Status</i> →</p>
Deleting all entries	<p>Tools → In PIM/Life menu, <i>Calendar</i> → Delete → <i>All Appointments</i> → Yes →</p>
Deleting entries by specifying week (Week View)	<p>[Start Here] → Tools → In PIM/Life menu, <i>Calendar</i> → See below</p> <p><b>Within One Week</b></p> <p>Select date → Delete → <i>All This Week</i> → Yes →</p>
	<p><b>Up to the End of Previous Week</b></p> <p>Select date → Delete → <i>Up to Last Week</i> → Yes →</p>
Deleting entries by specifying month (1Month/3Month/6Month View)	<p>[Start Here] → Tools → In PIM/Life menu, <i>Calendar</i> → See below</p> <p><b>Within One Month</b></p> <p>Select date → Delete → <i>All This Month</i> → Yes →</p>
	<p><b>Up to the End of Previous Month</b></p> <p>Select date → Delete → <i>Up to Last Month</i> → Yes →</p> <p>• Not available in 6Month View.</p>

Deleting entries in six months (6Month View)

Tools → In PIM/Life menu, *Calendar* → Delete → *All This 6Months* → Yes →

## Tasks

### Task List

Hiding tasks	<p>Tools → In PIM/Life menu, <i>Tasks</i> → Select task → Edit → <i>Secret:</i> → On →</p>
--------------	--

### Saving/Editing Tasks

Editing tasks	<p>Tools → In PIM/Life menu, <i>Tasks</i> → Select task → Edit → Select item → Edit in the same manner as saving tasks →</p>
Setting priority	<p>Tools → In PIM/Life menu, <i>Tasks</i> → Select task → Edit → <i>Priority:</i> → Select priority →</p>
Changing Alarm tone/video & duration	<p>[Start Here] → Tools → In PIM/Life menu, <i>Tasks</i> → Select task → Edit → <i>Alarm:</i> → See below</p> <p><b>Alarm Tone/Video</b></p> <p><i>Assign Tone/Video:</i> → Select folder → Select tone/file →</p> <p>• Select start point if required.</p> <p><b>Duration</b></p> <p><i>Duration:</i> → Select time →</p>
Changing Alarm volume	<p>Tools → In PIM/Life menu, <i>Tasks</i> → Alarm Settings → <i>Alarm Volume:</i> → Adjust level →</p>

Selecting Vibration option	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Tasks</b> ➔ ● ➔ ☰ ➔ <b>Alarm Settings</b> ➔ ● ➔ <b>Vibration:</b> ➔ ● ➔ <b>Select option</b> ➔ ●</p>
Changing illumination settings	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Tasks</b> ➔ ● ➔ ☰ ➔ <b>Alarm Settings</b> ➔ ● ➔ <b>Effect Illumination:</b> ➔ ● ➔ See below</p> <p><b>Setting Alarm Tone to Control Illumination</b>  <b>Switch On/Off</b> ➔ ● ➔ <b>Link to Sound</b> ➔ ● ➔ ☰</p> <p><b>Changing Illumination Pattern</b>  <b>Pattern/Color</b> ➔ ● ➔ <b>Select pattern</b> ➔ ● ➔ <b>Select color</b> ➔ ● ➔ ☰</p> <ul style="list-style-type: none"> <li>• Light color is unselectable for some patterns.</li> </ul> <p><b>Changing Key Illumination Pattern</b>  <b>Key Pattern</b> ➔ ● ➔ <b>Select pattern</b> ➔ ● ➔ ☰</p> <ul style="list-style-type: none"> <li>• Regardless of Key Pattern setting, ringtones control illumination when Switch On/Off is set to <b>Link to Sound</b>.</li> </ul> <p><b>Disabling Illumination</b>  <b>Switch On/Off</b> ➔ ● ➔ <b>Off</b> ➔ ● ➔ ☰</p>
Sounding Alarm tone even in Manner mode	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Tasks</b> ➔ ● ➔ ☰ ➔ <b>Alarm Settings</b> ➔ ● ➔ <b>For Manner Mode:</b> ➔ ● ➔ <b>Ring</b> ➔ ● ➔ <b>Yes</b> ➔ ●</p>

## Managing Tasks

Searching tasks	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Tasks</b> ➔ ● ➔ ☰ ➔ <b>Find</b> ➔ ● ➔ See below</p> <p><b>By Part of Subject</b>  <b>By Subject</b> ➔ ● ➔ Enter text ➔ ●</p> <p><b>By Due Date</b>  <b>By Due Date</b> ➔ ● ➔ Enter date ➔ ●</p>
Sorting tasks by priority	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Tasks</b> ➔ ● ➔ ☰ ➔ <b>Sort</b> ➔ ● ➔ <b>Priority</b> ➔ ●</p>
Checking memory status	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Tasks</b> ➔ ● ➔ ☰ ➔ <b>Memory Status</b> ➔ ●</p>
Deleting all tasks	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Tasks</b> ➔ ● ➔ ☰ ➔ <b>Delete</b> ➔ ● ➔ <b>All Tasks</b> ➔ ● ➔ <b>Yes</b> ➔ ●</p>

## Alarms

Editing entries	<ul style="list-style-type: none"> <li>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Alarms</b> ➔ ● ➔ <b>Select entry</b> ➔ ● ➔ <b>Select item</b> ➔ ● ➔ <b>Edit</b> in the same manner as saving entries ➔ ● ➔ (Y)</li> </ul>
Saving entry name	<ul style="list-style-type: none"> <li>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Alarms</b> ➔ ● ➔ <b>Select entry</b> ➔ ● ➔ <b>Subject:</b> ➔ ● ➔ <b>Enter name</b> ➔ ● ➔ (Y)</li> </ul>
Changing Alarm tone/video	<p>(Start Here) ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Alarms</b> ➔ ● ➔ <b>Select entry</b> ➔ ● ➔ <b>Assign Tone/Video:</b> ➔ ● ➔ See below</p> <p><b>Using Preset Tone or Data Folder File</b>  <b>Select folder</b> ➔ ● ➔ <b>Select tone/file</b> ➔ ● ➔ (Y)</p> <ul style="list-style-type: none"> <li>• Select start point if required.</li> </ul> <p><b>Using Customized Screen Tone/Video</b>  <b>Customized Screen</b> ➔ ● ➔ (Y)</p>
Setting handset to vibrate at Alarm Time	<ul style="list-style-type: none"> <li>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Alarms</b> ➔ ● ➔ <b>Select entry</b> ➔ ● ➔ <b>Vibration:</b> ➔ ● ➔ <b>On</b> or <b>Link to Sound</b> ➔ ● ➔ (Y)</li> <li>• Select <b>Link to Sound</b> to allow compatible SMAF files to control vibration.</li> </ul>

## Changing illumination settings

(Start Here) ● ➔ **Tools** ➔ ● ➔ In PIM/Life menu, **Alarm** ➔ ● ➔ **Select entry** ➔ ● ➔ **Effect Illumination:** ➔ ● ➔ See below

**Setting Alarm Tone to Control Illumination**  
**Switch On/Off** ➔ ● ➔ **Link to Sound** ➔ ● ➔ (Y) ➔ (Y)

**Changing Illumination Pattern**  
**Pattern/Color** ➔ ● ➔ **Select pattern** ➔ ● ➔ **Select color** ➔ ● ➔ (Y) ➔ (Y)

- Light color is unselectable for some patterns.

**Changing Key Illumination Pattern**  
**Key Pattern** ➔ ● ➔ **Select pattern** ➔ ● ➔ (Y) ➔ (Y)

- Regardless of Key Pattern setting, ringtones control illumination when Switch On/Off is set to **Link to Sound**.

**Disabling Illumination**  
**Switch On/Off** ➔ ● ➔ **Off** ➔ ● ➔ (Y) ➔ (Y)

## Sounding Alarm tone even in Manner mode

● ➔ **Tools** ➔ ● ➔ In PIM/Life menu, **Alarms** ➔ ● ➔ **Settings** ➔ ● ➔ **For Manner Mode** ➔ ● ➔ **Ring** ➔ ● ➔ **Yes** ➔ ●

## Activating Alarm based on World Clock time

● ➔ **Tools** ➔ ● ➔ In PIM/Life menu, **Alarms** ➔ ● ➔ **Settings** ➔ ● ➔ **Link to World Clk** ➔ ● ➔ **On** ➔ ●



## Wakeup TV

Editing entries	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Wakeup TV</b> ➔ ● ➔ <b>Select entry</b> ➔ ● ➔ <b>Select item</b> ➔ ● ➔ <b>Edit</b> in the same manner as saving entries ➔ Ⓜ</p>
Changing Alarm tone/video	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Wakeup TV</b> ➔ ● ➔ <b>Select entry</b> ➔ ● ➔ <b>Assign Tone/Video:</b> ➔ ● ➔ <b>See below</b></p> <p><b>Using Preset Tone or Data Folder File</b>  <b>Select folder</b> ➔ ● ➔ <b>Select tone/file</b> ➔ ● ➔ Ⓜ          • Select start point if required.</p> <p><b>Using Customized Screen Tone/Video</b>  <b>Customized Screen</b> ➔ ● ➔ Ⓜ</p>
Changing illumination settings	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Wakeup TV</b> ➔ ● ➔ <b>Select entry</b> ➔ ● ➔ <b>Effect Illumination:</b> ➔ ● ➔ <b>See below</b></p> <p><b>Setting Alarm Tone to Control Illumination</b>  <b>Switch On/Off</b> ➔ ● ➔ <b>Link to Sound</b> ➔ ● ➔ Ⓜ ➔ Ⓜ</p> <p><b>Changing Illumination Pattern</b>  <b>Pattern/Color</b> ➔ ● ➔ <b>Select pattern</b> ➔ ● ➔ <b>Select color</b> ➔ ● ➔ Ⓜ ➔ Ⓜ          • Light color is unselectable for some patterns.</p> <p><b>Changing Key Illumination Pattern</b>  <b>Key Pattern</b> ➔ ● ➔ <b>Select pattern</b> ➔ ● ➔ Ⓜ ➔ Ⓜ          • Regardless of Key Pattern setting, ringtones control illumination when Switch On/Off is set to <b>Link to Sound</b>.</p> <p><b>Disabling Illumination</b>  <b>Switch On/Off</b> ➔ ● ➔ <b>Off</b> ➔ ● ➔ Ⓜ ➔ Ⓜ</p>

Sounding Alarm tone even in Manner mode

● ➔ **Tools** ➔ ● ➔ In PIM/Life menu, **Wakeup TV** ➔ ● ➔ **For Manner Mode** ➔ ● ➔ **Ring** ➔ ● ➔ **Yes** ➔ ●

## Household Accounts

Renaming icon labels	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Household Accounts</b> ➔ ● ➔ <b>Select manual input panel</b> ➔ ● ➔ <b>See below</b></p> <p><b>Shops</b>  <b>Shop</b> ➔ ● ➔ <b>Select icon</b> ➔ ☒ ➔ <b>Enter name</b> ➔ ●</p> <p><b>Payment Methods</b>  <b>Paid</b> ➔ ● ➔ <b>Select icon</b> ➔ ☒ ➔ <b>Enter name</b> ➔ ●</p> <p><b>Categories</b>  <b>Category Change</b> ➔ ● ➔ <b>Select icon</b> ➔ ☒ ➔ <b>Enter name</b> ➔ ●</p>
Importing Household Accounts data	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Household Accounts</b> ➔ ● ➔ ☒ ➔ <b>Import All</b> ➔ ● ➔ <b>Select file</b> ➔ ● ➔ <b>Yes</b> ➔ ●          • Current Household Accounts data is overwritten.</p>
Exporting Household Accounts data	<p>● ➔ <b>Tools</b> ➔ ● ➔ In PIM/Life menu, <b>Household Accounts</b> ➔ ● ➔ ☒ ➔ <b>Export All</b> ➔ ● ➔ <b>Yes</b> ➔ ●          • Data is exported as a CSV file and saved to handset Data Folder (Other Documents).          • Files are saved to Memory Card, if inserted.</p>

## Calculator

Copying calculation results	While result appears,  ➔ <i>Copy</i> ➔
Changing exchange rate for currency conversion	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Calculator</i> ➔  ➔ <i>Money Converter</i> ➔  ➔ <i>Exchange Rate</i> ➔  ➔ <i>Domestic or Foreign</i> ➔  ➔ <i>Enter rate</i> ➔
Converting currencies	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Calculator</i> ➔  ➔ <i>Enter amount of money</i> ➔  ➔ <i>Money Converter</i> ➔  ➔ <i>To Domestic or To Foreign</i> ➔ • Set Exchange Rate first.

## Expenses Memo

Changing Category of saved entry	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Expenses Memo</i> ➔  ➔ <i>Select list</i> ➔  ➔ <i>Select entry</i> ➔  ➔ <i>Select Category</i> ➔
Changing amount	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Expenses Memo</i> ➔  ➔ <i>Select list</i> ➔  ➔ <i>Select entry</i> ➔  ➔ <i>Change Amount</i> ➔  ➔ <i>Edit</i> ➔
Renaming Categories	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Expenses Memo</i> ➔  ➔ <i>Edit Category</i> ➔  ➔ <i>Select Category</i> ➔  ➔ <i>Enter name</i> ➔

## Osaifu-Keitai®

Enabling to view e-money balances	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Osaifu-Keitai</i> ➔  ➔ <i>IC Card Settings</i> ➔  ➔ <i>Balance Info</i> ➔  ➔ <i>&lt;Empty&gt;</i> ➔  ➔ <i>Lifestyle-Appli or SI Appli</i> ➔  ➔ <i>Select application</i> ➔ • For use with compatible Lifestyle-Applications. • Start Lifestyle-Appli once before adding it to Balance Info list.
Moving applications up/down Balance Info list	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Osaifu-Keitai</i> ➔  ➔ <i>IC Card Settings</i> ➔  ➔ <i>Balance Info</i> ➔  ➔ <i>Select application</i> ➔  ➔ <i>Move</i> ➔  ➔ <i>Select target location</i> ➔
Removing applications from Balance Info list	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Osaifu-Keitai</i> ➔  ➔ <i>IC Card Settings</i> ➔  ➔ <i>Balance Info</i> ➔  ➔ <i>Select application</i> ➔  ➔ <i>Delete</i> ➔
Customizing handset response to reader/writer commands	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Osaifu-Keitai</i> ➔  ➔ <i>IC Card Settings</i> ➔  ➔ <i>Interface Settings</i> ➔  ➔ <i>Select item</i> ➔  ➔ <i>Off</i> ➔
Opening IC Card properties	➔ <i>Tools</i> ➔  ➔ In PIM/Life menu, <i>Osaifu-Keitai</i> ➔  ➔ <i>IC Card Settings</i> ➔  ➔ <i>IC Card Status</i> ➔



## Hour Minder

## Changing Hour Minder tone/video

● → **Tools** → ● → ⌚ **Clock/Gauge** → **Hour Minder** → ● → **Advanced** → ● → **Assign Tone/Video:** → ● → **Select folder** → ● → **Select tone/file** → ● → ⌚ → ⌚

- Select start point if required.

## Setting handset to vibrate at Hour Minder Time

● → **Tools** → ● → ⌚ **Clock/Gauge** → **Hour Minder** → ● → **Advanced** → ● → **Vibration:** → ● → **On or Link to Sound** → ● → ⌚ → ⌚

- Select **Link to Sound** to allow compatible SMAF files to control vibration.

## Changing illumination settings

**Start Here** ● → **Tools** → ● → ⌚ **Clock/Gauge** → **Hour Minder** → ● → **Advanced** → ● → **Effect Illumination:** → ● → **See below**

**Setting Alarm Tone to Control Illumination**  
**Switch On/Off** → ● → **Link to Sound** → ● → ⌚ → ⌚ → ⌚

**Changing Illumination Pattern**  
**Pattern/Color** → ● → **Select pattern** → ● → **Select color** → ● → ⌚ → ⌚ → ⌚

- Light color is unselectable for some patterns.

**Changing Key Illumination Pattern**  
**Key Pattern** → ● → **Select pattern** → ● → ⌚ → ⌚

- Regardless of Key Pattern setting, ringtones control illumination when Switch On/Off is set to **Link to Sound**.

**Disabling Illumination**  
**Switch On/Off** → ● → **Off** → ● → ⌚ → ⌚

## Sounding Hour Minder tone even in Manner mode

● → **Tools** → ● → ⌚ **Clock/Gauge** → **Hour Minder** → ● → **Advanced** → ● → **For Manner Mode:** → ● → **Ring** → ● → **Yes** → ● → ⌚

## Activating Hour Minder based on World Clock time

● → **Tools** → ● → ⌚ **Clock/Gauge** → **Hour Minder** → ● → **Advanced** → ● → **Link to World Clk:** → ● → **On** → ● → ⌚ → ⌚

## Pedometer

## Using Pedometer Calendar

● → **Tools** → ● → ⌚ **Clock/Gauge** → **Pedometer** → ● → ⌚ → **Select date** → ●

- Degree of achievement appears.
- Press **X** or **#** to view previous or next month.

## Checking accumulated data

● → **Tools** → ● → ⌚ **Clock/Gauge** → **Pedometer** → ● → ☐ → **Accumulated Data** → ●

- Change in body information is reflected in the data.

## Resetting accumulated data

● → **Tools** → ● → ⌚ **Clock/Gauge** → **Pedometer** → ● → ☐ → **Accumulated Data** → ● → ☐ → **Reset Walk Data** → ● → **Yes** → ●

- Averages are also reset.

## Setting daily step count reset time

● → **Tools** → ● → ⌚ **Clock/Gauge** → **Pedometer** → ● → ☐ → **Settings** → ● → **Count Reset Time** → ● → **Enter time** → ● → **Yes** → ●

Customizing achievement notice	<b>Start Here</b> → <b>Tools</b> → <b>Clock/Gauge</b> → <b>Pedometer</b> → <b>Settings</b> → <b>Target</b> → <b>Goal Announce</b> → <b>On</b> → <b>See below</b>
	<b>Changing Tone</b> <b>Goal Sound</b> → Select pattern
	<b>Changing Tone Volume</b> <b>Goal Volume</b> → Adjust level
	<b>Selecting Vibration Option</b> <b>Vibration</b> → Select option
	<b>Changing Duration</b> <b>Duration</b> → Select time • For custom Duration, select <b>Other</b> and press .

## S! GPS Navi

Sending current location via mail	<b>Tools</b> → <b>Clock/Gauge</b> → <b>S! GPS Navi</b> → <b>Location Mail</b> → <b>Positioning complete</b> → <b>Complete message</b> • When accuracy level is 1 or 2, choose <b>No</b> and press after positioning, then complete message.
	<b>Start Here</b> → <b>Tools</b> → <b>Clock/Gauge</b> → <b>S! GPS Navi</b> → <b>NAVI Settings</b> → <b>Map URL Settings</b> → <b>See below</b>
Changing map source URL	<b>Adding URLs</b> <b>&lt;Not set&gt;</b> → Enter URL
	<b>Setting Destination URL</b> <b>Select URL</b>
	<b>Viewing/Editing/Deleting URLs</b> <b>Select URL</b> → <b>Display, Edit or Delete</b> • Follow onscreen prompt.

Disabling positioning	<b>Tools</b> → <b>Clock/Gauge</b> → <b>S! GPS Navi</b> → <b>NAVI Settings</b> → <b>Positioning Lock</b> → <b>On</b> • Handset Code is required to re-select <b>Off</b> .
Selecting Location Information transmission option	<b>Tools</b> → <b>Clock/Gauge</b> → <b>S! GPS Navi</b> → <b>NAVI Settings</b> → <b>Send Location Info</b> → Select option
Using My Location & Location Log	<b>Start Here</b> → <b>Tools</b> → <b>Clock/Gauge</b> → <b>S! GPS Navi</b> → <b>My Location List or Location Logs</b> → Select entry or record → <b>See below</b>
	<b>Opening Map</b> <b>Yes</b>
	<b>Showing Routes via Navi Appli</b> <b>Go to</b> → <b>Yes</b> • Follow onscreen instructions.
	<b>Inserting into Message Text</b> <b>As Msg. Text</b> → <b>Complete message</b>
Saving Location Log records to My Location	<b>Saving to Phone Book</b> <b>Save to Ph.Book</b> → <b>As New Entry</b> → <b>Complete other fields</b> • To add to an existing entry, select <b>As New Detail</b> .
	<b>Tools</b> → <b>Clock/Gauge</b> → <b>S! GPS Navi</b> → <b>Location Logs</b> → <b>Select record</b> → <b>Set as My Location</b> → <b>Name</b> → Enter name
Deleting Location Log records	<b>Tools</b> → <b>Clock/Gauge</b> → <b>S! GPS Navi</b> → <b>Location Logs</b> → <b>Select record</b> → <b>Delete or Delete All</b> → <b>Yes</b> • Omit record selection step when deleting all records.

Suppressing  
Information window  
after sending  
Location Information  
automatically

● → *Tools* → ● → ⌚ *Clock/Gauge* → *SI GPS Navi* → ● → *NAVI Settings* → ● → *Inform Location* → ● → *Do not Show* → ●

## Notepad

Editing Notepad

*Start Here* ● → *Tools* → ● → ⌚ *Doc./Rec.* → *Notepad* → ● → *Select entry* → ☰ → *See below*

### Editing Text

*Edit Text* → ● → *Edit* → ●

### Changing Category

*Change Category* → ● → *Select Category* → ●

Searching text  
within all entries

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Notepad* → ● → *Select entry* → ☰ → *Search* → ● → *Enter text* → ●

Inserting Notepad  
text into message  
text

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Notepad* → ● → *Select entry* → ☰ → *Send* → ● → *As Message Text* → ● → *SI Mail or SMS* → ● → *Complete message* → ☑  
● SI Mail Composition window opens automatically depending on character count.

Sending entries via  
SI Mail

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Notepad* → ● → *Select entry* → ☰ → *Send* → ● → *Via Message* → ● → *Complete message* → ☑

Creating text files

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Notepad* → ● → *Select entry* → ☰ → *Setting/Manage* → ● → *Create Text File* → ● → *Enter name* → ● → *Save here* → ●

Importing text files

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Notepad* → ● → *Select entry* → ☰ → *Setting/Manage* → ● → *Import Text File* → ● → *Select file* → ●

Checking memory  
status

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Notepad* → ● → *Select entry* → ☰ → *Setting/Manage* → ● → *Memory Status* → ●

Opening properties

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Notepad* → ● → *Select entry* → ☰ → *Details* → ●

## Voice Recorder

Saving longer  
recordings

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Voice Recorder* → ● → ☰ → *Record Time* → ● → *Extended Voice* → ● → ● → *Recording starts* → ● → *Recording ends*  
● Insert Memory Card to record in *Extended Voice* mode. (Recording is saved automatically.)

Sending Voice files  
via SI Mail

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Voice Recorder* → ● → ● → *Recording starts* → ● → *Recording ends* → *Save and Send* → ● → *Complete message* → ☑  
● Available in *For Message* mode.

Switching storage  
media

● → *Tools* → ● → ⌚ *Doc./Rec.* → *Voice Recorder* → ● → ☰ → *Save Recording to* → ● → *Select option* → ●  
● Available in *For Message* mode.  
● Set to *Ask Each Time* to select media after every recording.

Scan Barcode	
Scanning during text entry	<p><b>Start Here</b> In a text entry window,    <b>Scan</b> <b>Scan Code</b> <b>Frame barcode in center of Display</b> <b>See below</b></p> <p><b>Pasting All Scan Results</b></p> <p> <b>Pasting a Part of Scan Results</b></p> <p> <b>Select first character</b> <b>Highlight text range</b> </p>
	<p> <b>Tools</b> <b>Doc./Rec.</b> <b>Barcode/Scan</b> <b>Scan Barcode</b> <b>Continuous Scan</b> <b>On</b> <b>Frame barcode in center of Display</b> </p> <ul style="list-style-type: none"> <li>Choose <b>Yes</b> to continue scanning or <b>No</b> and press  to view scan results.</li> </ul>
Reading saved barcode images	<p> <b>Tools</b> <b>Doc./Rec.</b> <b>Barcode/Scan</b> <b>Open Barcode</b> <b>Select file</b> </p>
Saving scan results	<p> <b>Tools</b> <b>Doc./Rec.</b> <b>Barcode/Scan</b> <b>Scan Barcode</b> <b>Frame barcode in center of Display</b> <b>Save</b> </p>
Saving to Notepad	<p> <b>Tools</b> <b>Doc./Rec.</b> <b>Barcode/Scan</b> <b>Scan Barcode</b> <b>Frame barcode in center of Display</b> <b>Notepad</b> </p>

## Saving linked info to Phone Book

**Tools** **Doc./Rec.** **Barcode/Scan** **Scan Barcode** **Frame barcode in center of Display** **Select number or mail address** **Save to Ph.Book** **As New Entry** **Complete other fields**

- To add to an existing entry, select **As New Detail**.
- When **MEMORY:** appears in scan results, press to enter the items underlined with a dotted line automatically in Phone Book entry window.

## Opening saved scan results

**Tools** **Doc./Rec.** **Barcode/Scan** **Scanned Results** **Select file**

- Select a file and press to rename files, open properties or delete files.
- Some files may not open.

## Using linked info

**Start Here** **Tools** **Doc./Rec.** **Barcode/Scan** **Scan Barcode** **Frame barcode in center of Display** **See below**

## Dialing Numbers

Select phone number

## Sending Messages

Select mail address **Complete message**

- When **MAILTO:** appears in scan results, press to enter the items underlined with a dotted line automatically in Mail Composition window. (**SUBJECT:** or **BODY:** must be included to enter subject/message text.)

## Accessing Internet Sites

Select URL

Using images as Wallpaper	<p>  → <b>Tools</b> →  → <b>Doc./Rec.</b> →  → <b>Barcode/Scan</b> →  → <b>Scan Barcode</b> →  → <b>Frame barcode in center of Display</b> →  → <b>Select image</b> →  → <b>Set as Wallpaper</b> →  → <b>Vertical or Horizontal</b> </p> <ul style="list-style-type: none"> <li>For images smaller or larger than Display, Wallpaper Display options appear; follow onscreen prompts.</li> </ul>
Saving images & melodies	<p>  → <b>Tools</b> →  → <b>Doc./Rec.</b> →  → <b>Barcode/Scan</b> →  → <b>Scan Barcode</b> →  → <b>Frame barcode in center of Display</b> →  → <b>Select file</b> →  → <b>To Data Folder</b> </p>
Opening or playing files	<p>  → <b>Tools</b> →  → <b>Doc./Rec.</b> →  → <b>Barcode/Scan</b> →  → <b>Scan Barcode</b> →  → <b>Frame barcode in center of Display</b> →  → <b>Select file</b> </p>
Using images for System Graphics	<p>  → <b>Tools</b> →  → <b>Doc./Rec.</b> →  → <b>Barcode/Scan</b> →  → <b>Scan Barcode</b> →  → <b>Frame barcode in center of Display</b> →  → <b>Select image</b> →  → <b>As System</b> →  → <b>Select item</b> →  → <b>Specify image area</b> </p> <ul style="list-style-type: none"> <li>Some images may be usable without specifying image area.</li> </ul>

Pasting to message text	<p>  → <b>Start Here</b> →  → <b>Tools</b> →  → <b>Doc./Rec.</b> →  → <b>Barcode/Scan</b> →  → <b>Scan Barcode</b> →  → <b>Frame barcode in center of Display</b> →  → <b>Send Message</b> →  → <b>See below</b> </p> <p><b>All Text</b></p> <p>  → <b>S! Mail or SMS</b> →  → <b>Complete message</b> </p> <ul style="list-style-type: none"> <li>S! Mail Composition window opens automatically depending on character count.</li> </ul> <p><b>Selected Text</b></p> <p>  → <b>Select first character</b> →  → <b>Highlight text range</b> →  → <b>S! Mail or SMS</b> →  → <b>Complete message</b> </p> <ul style="list-style-type: none"> <li>S! Mail Composition window opens automatically depending on character count.</li> </ul>
Copying text	<p>  → <b>Start Here</b> →  → <b>Tools</b> →  → <b>Doc./Rec.</b> →  → <b>Barcode/Scan</b> →  → <b>Scan Barcode</b> →  → <b>Frame barcode in center of Display</b> →  → <b>See below</b> </p> <p><b>Text</b></p> <p>  → <b>Copy</b> →  → <b>Select first character</b> →  → <b>Highlight text range</b> </p> <p><b>Number, Address or URL</b></p> <p> <b>Select number, mail address or URL</b> →  → <b>Copy Telephone, Copy Address or Copy URL</b> </p>



Scan Card	
Saving to Notepad	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Card</b> ➔ ● ➔ Frame card in center of Display ➔ ● ➔ ● ➔ ☒ ➔ <b>Notepad</b> ➔ ●</p>
Pasting to message text	<p>☐ <b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Card</b> ➔ ● ➔ Frame card in center of Display ➔ ● ➔ ● ➔ ☒ ➔ <b>Send Message</b> ➔ ● ➔ See below</p> <p><b>All Text</b></p> <p>● ➔ <b>S! Mail or SMS</b> ➔ ● ➔ Complete message ➔ ☒</p> <ul style="list-style-type: none"> <li>S! Mail Composition window opens automatically depending on character count.</li> </ul> <p><b>Selected Text</b></p> <p>☒ ➔ Select first character ➔ ● ➔ Highlight text range ➔ ● ➔ <b>S! Mail or SMS</b> ➔ ● ➔ Complete message ➔ ☒</p> <ul style="list-style-type: none"> <li>S! Mail Composition window opens automatically depending on character count.</li> </ul>
Copying text	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Card</b> ➔ ● ➔ Frame card in center of Display ➔ ● ➔ ● ➔ ☒ ➔ <b>Copy</b> ➔ ● ➔ Select first character ➔ ● ➔ Highlight text range ➔ ●</p>

Scan Text	
Scanning and pasting during text entry	<p>In a text entry window, ☒ ➔ <b>Scan</b> ➔ ● ➔ <b>Scan Text</b> ➔ ● ➔ Frame text in center of Display ➔ ● ➔ Select line ➔ ● ➔ ●</p>
Scanning more text	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Text</b> ➔ ● ➔ Frame text in center of Display ➔ ● ➔ Select line ➔ ● ➔ ● ➔ ☒ ➔ <b>Continue Part or Scan More</b> ➔ ●</p> <ul style="list-style-type: none"> <li>Select <b>Continue Part</b> to enter additional text or <b>Scan More</b> to enter text after a line break.</li> </ul>
Saving scan results	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Text</b> ➔ ● ➔ Frame text in center of Display ➔ ● ➔ Select line ➔ ● ➔ ● ➔ ☒ ➔ <b>Save</b> ➔ ●</p>
Saving linked info to Phone Book	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Text</b> ➔ ● ➔ Frame text in center of Display ➔ ● ➔ Select line ➔ ● ➔ ● ➔ Select number or mail address ➔ ☒ ➔ <b>Save to Ph.Book</b> ➔ ● ➔ <b>As New Entry</b> ➔ ● ➔ Complete other fields ➔ ☒</p> <ul style="list-style-type: none"> <li>To add to an existing entry, select <b>As New Detail</b>.</li> </ul>
Opening saved scan results	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scanned Results</b> ➔ ● ➔ Select file ➔ ●</p> <ul style="list-style-type: none"> <li>Select a file and press ☒ to rename files, open properties or delete files.</li> <li>Some files may not open.</li> </ul>

Using linked info	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ ● ➔ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Text</b> ➔ ● ➔</p> <p>Frame text in center of Display ➔ ● ➔ <b>Select line</b> ➔ ● ➔ ● ➔ See below</p>
	<p><b>Dialing Numbers</b></p> <p>Select phone number ➔ ● ➔ </p>
	<p><b>Sending Messages</b></p> <p>Select mail address ➔ ● ➔ Complete message ➔ </p>
	<p><b>Accessing Internet Sites</b></p> <p>Select URL ➔ ●</p>
Pasting to message text	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ ● ➔ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Text</b> ➔ ● ➔</p> <p>Frame text in center of Display ➔ ● ➔ <b>Select line</b> ➔ ● ➔ ● ➔  ➔ <b>Send Message</b> ➔ ● ➔ ➔ See below</p>
	<p><b>All Text</b></p> <p>● ➔ <b>S! Mail or SMS</b> ➔ ● ➔ Complete message ➔ </p> <ul style="list-style-type: none"> <li>• S! Mail Composition window opens automatically depending on character count.</li> </ul>
	<p><b>Selected Text</b></p> <p> ➔ Select first character ➔ ● ➔ Highlight text range ➔ ● ➔ <b>S! Mail or SMS</b> ➔ ● ➔ Complete message ➔ </p> <ul style="list-style-type: none"> <li>• S! Mail Composition window opens automatically depending on character count.</li> </ul>

Copying text	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ ● ➔ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Text</b> ➔ ● ➔</p> <p>Frame text in center of Display ➔ ● ➔ <b>Select line</b> ➔ ● ➔ ● ➔ See below</p>
	<p><b>Text</b></p> <p> ➔ <b>Copy</b> ➔ ● ➔ Select first character ➔ ● ➔ Highlight text range ➔ ●</p>
	<p><b>Number, Address or URL</b></p> <p>Select number, mail address or URL ➔  ➔ <b>Copy Telephone, Copy Address or Copy URL</b> ➔ ●</p>

### Kanji/English Grabber


Scanning and pasting during text entry	<p>In a text entry window,  ➔ <b>Scan</b> ➔ ● ➔ <b>Kanji/English Grabber</b> ➔ ● ➔ Frame word in Loupe ➔ ● ➔ Scan results appear ➔ ●</p>
--	--

## Osaifu-Keitai®

### ? Cannot use Osaifu-Keitai® (S! FeliCa)

- Battery may be low. Charge battery or install a charged battery.

### ? Recognition via reader/writer takes time

- Check  logo area. Foreign articles can block/hamper recognition.

### ? Call Remote Lock does not activate even after specified number of Missed Calls

- Missed Call count is reset by calls from other numbers. If series is interrupted, start over from the beginning.
- When Call Forwarding is active, Missed Calls may not be recorded.

## Wakeup TV

### ? TV does not activate with specified channel

- If Wakeup TV Time arrives while TV is active, channel does not switch to the specified one.

## Voice Recorder

### ? Cannot record properly

- If incompatible microphone is connected, recording may fail.

### ? Noise/skipping occurs

- Avoid shocks to handset while recording; may cause noise or skipping.

### ? Recording takes time to start

- Recording window may take longer to open as more Voice files are saved on Memory Card.

## Scanning Barcode/Card/Text

### ? Cannot read barcodes properly

- Scan may fail if barcode is dirty or unclear.
- Scan may fail if barcode is scanned under inadequate light.
- Scan may fail if multiple barcodes are captured at one time.

### ? Cannot read barcodes during text entry

- Scanning is not available during calls or when mobile camera is active.

### ? Cannot read split QR Codes in Data Folder automatically

- When scan fails, follow onscreen instructions and select next barcode image manually.

### ? Cannot scan business cards properly

- Scan fails if business card is printed in light-colored text on a dark background, handwritten or printed in casual/ decorative fonts, decorated with a background pattern, or designed with both vertical and horizontal text.
- Scan may fail if business card is printed in light-colored text on a light background, printed in italics or extremely small fonts, decorated with a logo or logo-like text, printed on a glossy paper or other material, or dirty/folded.

### ? Cannot scan text properly

- Scanning over 35 characters at one time may yield poor results.
- In Line mode, adjust to frame text in [ ]. Letters at the ends may be distorted.