S! Quick News	12-2
Receiving Content Updates	
(Japanese)	. 12-2
S! Information Channel	12-3
S! Information Channel & Weather	
Indicator (Japanese)	12-3
Content Downloads	12-4
Downloading Content (Japanese)	. 12-4
e-Books	12-5
Reading e-Books (Japanese)	12-5

S! Friend's Status	12-6
Using S! Friend's Status	12-6
S! Circle Talk	12-9
Using S! Circle Talk	12-9
Blog Tool	12-11
Blogging	12-11
Additional Functions	12-13
Troubleshooting	12-17

# 12

Entertainment



## Receiving Content Updates (Japanese)

View content updates or breaking news. Packet transmission fees apply (except when downloading via Wi-Fi).


#### **Registering S! Quick News Items**







S! Quick News List



Handset connects to the Internet.



Follow onscreen instructions

#### **Opening Information**

- In S! Quick News List, select item **→** (•)
  - Title list appears.



- Information appears.
- Press (22) to return to title list, or (32) to open next title.

#### **Updating Items Manually**

[S! Quick News List] Select item ▶ (y) **→ 更新 → () → 一件** or **全件 → ()** 

	Indicators		
<b>©</b>	Unread Special news		Unread General news
(c)	Read Special news		Read General news
1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	Unread News Flash	×	Auto update disabled
**	Read News		



## S! Information Channel & Weather Indicator (Japanese)

Subscribe to Japanese mobile periodicals that download to handset automatically; use Weather Indicator as needed. Packet transmission fees apply.

#### Service Registration & Content Subscription





St Information Channel Menu



## 



 Handset connects to the Internet. Follow onscreen instructions.

#### **New Received Information**

Information window opens for new S! Information Channel info delivery.

- While Information window appears, S! Info. Channel **→** (•)
  - S! Information Channel page opens. Follow onscreen instructions
  - S! Information Channel page handling is similar to that of Yahoo! Keitai



## Standby returns

**Opening Unread Latest Issue** [S! Information Channel Menu] What's New 

●

**Opening Back Issues** 

[S! Information Channel Menu] Back Issue 

Select date 

O

#### Using Weather Indicator

After S! Information Channel registration. local area weather indicator appears in Standby.

#### Manual Update

[S! Information Channel Menu] Weather Indicator 

◆ 

● 

Manual Update → ● Yes → ●





## **Downloading Content (Japanese)**

Download media content via Yahoo! Keitai.

#### **Via Free Content Providers**

Download free Graphic Mail templates, e-Books, games, etc.

Content downloads are free, however, they require Internet connection incurring packet transmission fees (except when downloading via Wi-Fi).





● **Entertainment ●** ●





Entertainment Menu

- - Free Contents **→** ●





- Select provider **→**
- Handset connects to the Internet. Follow onscreen instructions.

#### Via S! Contents Store



 Handset connects to the Internet. Follow onscreen instructions.



## Reading e-Books (Japanese)

#### Downloading e-Books





Entertainment **→** (●)





Entertainment Menu



#### S! Contents Store ◆



- Handset connects to the Internet Follow onscreen instructions
- Downloaded e-Books are saved to Data Folder (Books).

#### Note

 Alternatively, go to SH-web Mobile Internet site (シャープ・メーカーサイトSH-web in Bookmarks; see P.6-9) for e-Books.

Downloading Free e-Books In ②, Free Contents → • • → 

Follow onscreen instructions.

#### e-Book Viewer

Read XMDF books and dictionary files. Some files may not be supported.

In Entertainment menu, e-Book Viewer **→** (•)

> · e-Book Viewer starts. Refer to the e-Book Viewer help menu for operational instructions.

#### Digital Media Viewer

Read digital magazines and newspapers. Some files may not be supported.



 Digital Media Viewer starts. Refer to the Digital Media Viewer help menu for operational instructions.

#### BookSurfing®

Download Contents Kevs and read CCF files. Some files may not be supported.



 BookSurfing<sup>®</sup> S! Application starts. Refer to the BookSurfing® help menu for operational instructions.

#### Moving CCF Files via Memory Card

 When purchasing a new handset, move CCF files and retrieve Contents Kevs to open the files. Some files may need to be re-downloaded



Exchange current usage status, mood, etc. with compatible handsets.

- Save and organize members in Groups.
- S! Friend's Status requires a separate contract and basic monthly fee.
- Set IP Service Setting to On.
- Set Connection status to Online

#### First S! Friend's Status Use

Follow these steps to register a number saved in Phone Book; Status, Availability and Comment are sent to the members.





Yes **▶** (•)



- Yes **→** (•)
- Phone Book **→** •
- Select entry **→ ● →** Select phone number **→** (•)
  - one number is saved.



 Registration request is sent to the number.

#### When Request is Accepted

 An acceptance notice arrives; My Status is sent and member's status appears on handset.

#### Direct Entry

If IP Service Setting is Off

After ①, On → ② → S! Friend's Status **→ (•) →** From **(•)** 

• Omit number selection step if only



#### **Opening Member Status**

- - ⇒ S! Friend's Status ⇒ 
    •
  - **→** Select Group



Select member → ●

• Member status details appear.

#### When Cancellation Notice Arrives

 Member is deleted from S! Friend's Status member list.

#### **Changing My Status**

Follow these steps to change Status, Availability and Comment; new status is sent to the members.

- ● Entertainment ◆ ●
   ◆ S! Friend's Status ◆ ●
   ◆ 私の状況 ◆
  - Tibility Tamada Takako

    Tamoが決況

    Online

    Cetifん


    Answer Status

    Answer OK

    Reply OK

    Join OK

My Status Window





Status Template Window

- Select new Status ▶ ●
- Select Availability, e.g.,

  Answer OK → Select

  new Availability → ●
- <Add Comment> → → Enter text → ●
- 🕞 <section-header> Þ Update starts

Changing Connection Status
[My Status Window] Online (or
Offline) → ● Select status → ●

Changing Status Icon/Label
[Status Template Window] Select
Status → ※ → Status Icon or Status
Label → ● → Select Pictogram or
enter text → ● ※ ※

Changing Availability Settings at Once
In ②, Answer Status ▶ ● ➤ Select
new Answer Status ▶ ● ➤ From ⑤
Editing My Status Name

Avoiding Member Image Reception
[My Status Window] ⊚ → Settings
→ ● → Receiving Image → ● →
Reject → ●



#### Receiving Request from Unsaved **Numbers**

When a registration request arrives, a confirmation appears.





 Acceptance notice is sent; the number is registered.

#### Rejecting

In  $\bigcirc$ , No  $\Rightarrow$   $\bigcirc$   $\Rightarrow$  Yes  $\Rightarrow$   $\bigcirc$ 

- Rejection notice is sent; the number cannot be registered for 24 hours.
- For *ConfirmLater*, Information window opens.

#### **Creating Status Templates**

Save custom combinations of Status Icon and Status Label to each template.



- In Status Template window,
- Enter name **→** •
- <未定> ▶ ●
- Status Icon → Select Pictogram **→ ●**
- Status Label 

  ◆ 

  Enter text **→** (**•**) **→** (**Y**?)
- Repeat € 5 → 🖅 → Saved

#### Saving to Data Folder

[Status Template Window] Select template → 🖾 → Save to DF → 💿 Save here ⇒ ●

Loading Templates via Data Folder [Status Template Window] 

→ Add Template 

Select template **▶ (0**)

**Renaming Templates** [Status Template Window] Select

**→** • **→** Enter name **→** •




## Using S! Circle Talk

Use handset like a walkie-talkie to speak to multiple parties simultaneously.

- A subscription to S! Friend's Status is required.
- Packet transmission fees apply during S! Circle Talk
- Set IP Service Setting to On.

#### Registering Members

Follow these steps to register a number saved in Phone Book:



- When registering a member for the first time, member registration confirmation appears. Choose Yes and press ( ), then skip ahead to ( ).
- <Add New Entry> ▶ ●







- Select number, e.g., No.1:
- Phone Book **→** (•)
- Select entry **→ ● →** Select phone number **→ ●**



- Omit number selection step if only one number is saved.



Saving as Individuals In ③, Individual → ④ → 🖯 - 🕞 Saving from S! Friend's Status Member List In ⑤. Members List → ⑥ → Select member **→ ( ) → ( )** ■ Omit when *Individual* is selected in If IP Service Setting is Off After ①. On → ② → S! Circle Talk →

● From ②

#### **Initiating S! Circle Talk**

Follow these steps to send S! Circle Talk requests to members:

(First, set Connection status to *Online* (P.12-7).)





Select member or Group



- - S! Circle Talk starts when request is accepted by a receiver.
  - Loudspeaker activates automatically.

#### **Direct Entry**

Enter phone number  $\Rightarrow \bigcirc \Rightarrow Call$  S! Circle Talk  $\Rightarrow \bigcirc \Rightarrow \bigcirc$ 

#### S! Circle Talk Operations

- Speaking
- Press and hold when Press and Hold appears
  - → You have the floor



- **Turn** appears when you have the floor.
- Keep holding to speak
  → Release Floor is released
  - Warning tone sounds before time limit.

#### Incoming Calls during S! Circle Talk

 Incoming calls are rejected. Set handset to exit S! Circle Talk to answer incoming calls as needed.

# Canceling Loudspeaker During S! Circle Talk,

- To reactivate, follow these steps:
  - While message appears, ●

#### Exiting S! Circle Talk



 S! Circle Talk ends automatically when there is only one participant left, including yourself.

#### Rejoining S! Circle Talk

- Select most recent S! Circle
   Talk record → □ → Rejoin Circle
   Talk → ●
- Not available when S! Circle Talk has ended or maximum number of participants are already engaged.

#### **Accepting S! Circle Talk Request**

- While handset is ringing/ vibrating, ● → S! Circle Talk starts
  - Alternatively, press ...
  - S! Circle Talk Operations: left



## **Blogging**

Save blog details to view or update blogs easily on handset.

#### Saving Blog Details

Setup for Posting via Mail

Follow these steps to save blog name and address for posting:

**▶** Entertainment **▶** (●) ⇒ Blog Tool ⇒ 
•



**Blog Tool Window** 

Add New Entry 

◆ (●)



Blog Setting Menu

- Blog Title **→ ● →** Enter name **→** •
- Blog by send Mail **⇒** (●)



- Blog's Email Address ▶ ★ Enter mail address 
   ◆ ●

Saving Title/Text for Posts

After . Bloa's Title or Bloa's Text → ● Enter title or text → ● → ⑤

 Saved title/text is entered automatically when posting.

Setting Image Size for Posting After ⑤, Picture Size ▶ ⑥ ▶ Select size **→ ( )** 

Setup for Posting via the Internet Save URL for Yahoo! Keitai or PC sites, or both.

- In Blog Setting menu, Blog Title 

  ◆ 

  Enter name
- Refer/Send by Yahoo! Keitai or Refer/Send by PCSite/ Direct Browser 

  ◆ (●)




- Blog's URL → Enter URL **→ (•)**
- Refer Blog's URL → → Enter URL **→ ●**

#### **Posting to Blogs**

Complete setup for posting via mail/ Internet beforehand.

## Posting via Mail

- In Blog Tool window, select entry **→** (●)
- Blog by send Mail **→** • S! Mail Composition window opens
  - with address entered. • Omit @ if no URL is saved for posting.
- Complete message **▶** 🗹



- In Blog Tool window, select entry **→ ●**
- Blog by send Browser **→**
  - Page of URL saved in Blog's URL opens.
  - Omit @ if no address is saved for postina.
  - If PC Site Browser message appears, follow onscreen prompts.

When URLs for Yahoo! Keitai & PC Sites are Saved

After ②. select browser ▶ ●

#### **Opening Blog Page**

- In Blog Tool window, select entry 🗪 💬
  - Page of URL saved in Refer Blog's URL opens.
  - If PC Site Browser message appears, follow onscreen prompts.

When URLs for Yahoo! Keitai & PC Sites are Saved

After **①**, select browser **▶ ⊙** 





## S! Quick News

## ■ Opening/Updating Items

Setting S! Quick News automatic update	<ul> <li>Entertainment</li> <li>S! Quick News</li> <li>Settings</li> <li>Automatic Update</li> <li>Select item</li> <li>Select update</li> <li>Interval, On or Off</li> <li>If a message appears, press</li> <li>When selecting an item set to Off, a message appears.</li> <li>When Special is set to On, items are updated every four hours.</li> <li>When General is set to On, items are updated once a day.</li> <li>Updating items may incur high packet transmission fees.</li> <li>Only available in Japan.</li> </ul>	
Checking update schedule	● ★ Entertainment → ● ★ S! Quick News → Settings → ● ★ Check Schedule → ●	
Deleting Cl Oviel	Start Here	
Deleting S! Quick News items	One Entry           -# → ● → Yes → ●	
	All Entries 全件 → ● → Yes → ●	
Resetting S! Quick News List	Entertainment	

#### Other

Changing background image	● Entertainment ● S! Quick News ● Settings ● Change Skin ● Select pattern ● ●
Accessing source sites	<ul> <li>Entertainment</li> <li>S! Quick News</li> <li>S! Quick News List</li> <li>Select item</li> <li>Select title</li> <li>Select linked title</li> <li>Yes</li> </ul>
Disabling image download	● Entertainment ● ● S! Quick News ● Settings ● ● Show Image ● ● Off ●

## S! Information Channel

## ■ Receiving Information

Suppressing Information window for new received info	★ Entertainment       ★       S! Information     Channel/Weather       ★       Notification       ★       Off       ◆
Requesting re-delivery	● Entertainment → ● ⇒ S! Information Channel/Weather → ● ⇒ Get Latest Contents → ● → Yes → ●

#### ■ Information Pages

Changing Display Size	On a page, <sup>(a)</sup> → Settings → (b) → Display Size → (c) → Select size → (c)	
Changing scroll	On a page,	
unit	⇒ ● Select unit ⇒ ●	



Copying text	On a page, (□) → Copy Text → (●) → Select first character → (●) → Highlight text range → (●)
Saving files to Data Folder	On a page,  Save   Save   Select   Save   Save   Save   Select   Save   Save
Opening page properties	On a page,

#### ■ Weather Indicators

Checking weather forecast	Entertainment
Changing weather forecast page font size	On a page, ② → Settings → ● → Font Size →  ● → Select size → ●
Hiding Weather Indicator in Standby	● Entertainment ● S! Information Channel/Weather ● Weather Indicator ● Settings ● Standby Setting ● ● Off ●
Canceling Weather Indicator automatic updates	● Entertainment ● S! Information Channel/Weather ● Weather Indicator ● Settings ● Icon Update ● ● Off ● ●
Suppressing Information window for weather updates	● Entertainment ● S! Information Channel/Weather ● Weather Indicator ● Settings ● Weather Notif. ● ● Off ● ●

e-Books		
Copying text	In open page, ② ◆ 文字列を北' - ◆ ⑥ → Select first character ◆ ⑥ ◆ Highlight text range ◆ ⑥	
Opening non-945SH e-Books (Library)	Entertainment	
Using Library	Start Here ● → Entertainment → ● → e-Book  Viewer → ② → See below	
	Adding Folders	
	Switching Folders	
	Renaming Folders/Files Select folder/file → ② → Rename → ● → Enter name → ●	
	Moving Files Select file ⇒ ② → Move → ● Select folder ⇒ ● → Move here ⇒ ●	
	Deleting Folders/Files Select folder/file ⇒ ② ⇒ Delete ⇒ ● → Yes  ⇒ ●	
	Opening File Properties Select file	

## S! Friend's Status

## ■ Members & Groups

Adding members	<ul> <li>♠ Entertainment</li> <li>♠ ♦ S! Friend's Status</li> <li>♠ ♦ Select Group</li> <li>♠ ♦ Select method</li> <li>♠ ♦ Select entry or enter phone number</li> <li>♠ ♦ Yes</li> </ul>
Deleting members	● Entertainment ● S! Friend's Status ● ● Select Group Select member □ Registration Release ● Yes ●  Yes ● • Cancellation notice is sent; deleted members cannot be re-registered for 24 hours.
Moving members	● Entertainment ● ● S! Friend's Status ● ● Select Group ● Select member ● □ Change Group ● ● Select target Group ● ●
Renaming Groups	● Entertainment ● ● S! Friend's Status ● ● Select Group ● □ Edit Group Name ● ● Enter name ● ●
	Start Here
Rejecting requests	Rejecting Requests from Unsaved Numbers  Confirm if Registered  Rejection notice is sent to rejected numbers automatically.
	Rejecting All Requests  Always Ignore

## ■ Status & Availability

Saving custom Availability combinations	● Entertainment ● S! Friend's Status ● ● Settings ● Answer Status ● User Setting ● Select type ● Select Availability ● ♥ ❤
Changing Status Icon Pictogram or Status Label description	● Entertainment ● S! Friend's Status ● ◎ Settings ● Status Setting ● ③ Select template Select Status ● Status Icon ● Select Pictogram ● Status Label ● Enter text ● ⑨

## ■ Status Templates

Resetting templates	Start Here
	One Template  Select template   Reset   Yes  Page 1
	All Templates  ③ → Reset All → ● → Yes → ●

#### ■ Member Status & Notices

	<ul> <li>Entertainment</li> <li>S! Friend's Status</li> <li>Settings</li> <li>Status Update</li> </ul>
Opening notices	● Entertainment • ● S! Friend's Status • ● ● ⑤ Status Notif. List • ● Select notice • ●



## ■ My Details

	Description     Descripti
Sending My Details	→
	● ● ◆ ◆ Select Group ◆ Select member ◆ □ ◆ Send Image ◆ ● ◆ Yes ◆ ●
illage	Available when your handset number is saved in
	Phone Book on member's handset.

## S! Circle Talk

#### ■ Member List

	Start Here ● ⇒ Entertainment ⇒ ● ⇒ S! Circle  Talk ⇒ ● ⇒ Select member ⇒ □ ⇒ See below
Editing individual members	Replacing Members  Edit → ● → ● ⇒ Select method → ● →  Select entry → ●
	Deleting Members  Delete → ● → Yes → ●
	Start Here ● → Entertainment → ● → S! Circle  Talk → ● → Select Group → □ → See below
Editing Groups	Editing Group Name/Members  Edit → ● → Select target → ● Delit/enter  → ● → ♡
Editing Groups	Deleting Group Members  Edit → ● → Select member → ② → Delete →  ● → Yes → ● → ⊙
	Deleting Groups Delete → ● → Yes → ●

## ■ Settings

Disabling	Description     Descripti
Loudspeaker	● ⇒ 🖾 ⇒ Loudspeaker ⇒ ● ⇒ Off ⇒ ●
Exiting S! Circle	Description     Descripti
Talk for incoming	● ⇒ □ → Incoming Calls ⇒ ● → Voice Calls
calls	or Video Calls ⇒ ● → Accept Calls ⇒ ●

## Blog Tool

Editing entries	Description     Description
	⇒ Select entry ⇒ ⊚ ⇒ Edit ⇒ ● ⇒ Select
	item ⇒ ● ⇒ Edit/enter ⇒ ● ⇒ ∞ ⇒ ∞
	• For Blog Title, omit step of pressing after editing.
Deleting entries	▶ Entertainment → ● → Blog Tool → ● →
	Select entry ⇒ © ⇒ Delete ⇒ • Yes ⇒ •



#### S! Quick News



#### Cannot receive content updates

- Update may fail out-of-range or in poor signal conditions.
- Automatic Update does not affect S! Quick News List News Flash update items overnight.
- USIM Card replacement cancels Automatic Update.

#### S! Friend's Status



#### Cannot use S! Friend's Status

• Set IP Service Setting to On.



#### Handset rejected a registration request automatically

· Rejection notice is sent automatically when 30 members are already registered or handset fails to respond within two hours.



#### Registration request arrived from a deleted member

· Registration request arrives when a member fails to receive cancellation notice within 24 hours.



#### Registration request was sent to a member automatically

 Registration request is sent automatically when handset fails to receive rejection/ cancellation notice within 24 hours.



#### **Cannot create Status Templates**

• Three templates may already be added; reset one and retry.

#### S! Circle Talk



## Cannot use S! Circle Talk

• Set IP Service Setting to On.



#### S! Circle Talk starts automatically

 Check My Status; handset accepts S! Circle Talk requests automatically if S! Circle Talk Availability is set to Auto Join.



#### Cannot accept S! Circle Talk requests

· Check My Status; handset rejects S! Circle Talk requests automatically if S! Circle Talk Availability is set to Join NG.

